# NASA TECHNICAL NOTE

NASA TN D-3277

a. 1

# MASS-FLOW RATES AND TOTAL-PRESSURE RECOVERIES FOR A SEMICIRCULAR OPEN-NOSE INLET AT MACH 6

*by John S. Dennard and Lillian R. Boney*

*Langley Research Center*
*Langley Station, Hampton, Va.*

NATIONAL AERONAUTICS AND SPACE ADMINISTRATION • WASHINGTON, D. C. • MARCH 1966

NASA TN D-3277

MASS-FLOW RATES AND TOTAL-PRESSURE RECOVERIES

FOR A SEMICIRCULAR OPEN-NOSE INLET

AT MACH 6

By John S. Dennard and Lillian R. Boney

Langley Research Center
Langley Station, Hampton, Va.

NATIONAL AERONAUTICS AND SPACE ADMINISTRATION

# MASS-FLOW RATES AND TOTAL-PRESSURE RECOVERIES

## FOR A SEMICIRCULAR OPEN-NOSE INLET

## AT MACH 6

By John S. Dennard and Lillian R. Boney
Langley Research Center

## SUMMARY

An all-internal-compression inlet has been tested in a Mach 6 tunnel. The inlet was semicircular with provision for radiation cooling over much of the compression region; boundary-layer bleed was incorporated slightly upstream of the throat. A FORTRAN IV computer program employing the appropriate shock and characteristic equations was used to determine the inlet internal aerodynamic flow field. Pressure distributions in the supersonic diffuser were in good agreement with those predicted by the method of characteristics. The maximum total pressure in the subsonic diffuser was 18.7 percent of the free-stream total pressure, with a corresponding bleed flow rate of 11.3 percent. Maximum kinetic-energy efficiency was 91.5 percent, a level which is in the range of interest of practical engine applications.

## INTRODUCTION

The use of air-breathing engines in the hypersonic flow regime is being seriously considered because of the high theoretical specific impulse. Only chemical rockets have previously been used in the hypersonic flow regime. The inlet which supplies air to a hypersonic air-breathing engine will be required to operate at very high altitudes and velocities. Temperatures will reach very high values on leading edges and in regions such as the throat where the cross-sectional area is restricted and high pressures occur. Thus, the conventional requirements of high-pressure recovery and low drag are compounded by the cooling requirements in hypersonic atmospheric flight.

Two-dimensional all-internal-compression inlets have been tested and reported for Mach numbers from 1 to 6 in reference 1, for Mach numbers from 1.6 to 4.1 in reference 2, and for Mach number 6.9 in reference 3. In reference 4 is presented results of a three-dimensional axially symmetric all-internal-compression inlet tested at Mach number 5. Boundary-layer bleed flow rates for these investigations range between 5 and 30 percent of the total inlet mass flow. Results of reference 1 indicate that the

supersonic boundary-layer growth and large wetted areas are major problems in achieving high-pressure recovery in two-dimensional inlets and that the large wetted areas also present a major cooling problem for the internal surfaces of the inlet.

The internal flow performance of a three-dimensional semicircular inlet designed for radiation cooling throughout most of the compression region is discussed in the present paper. The inlet has essentially zero wave drag, and compared with other inlets, has a small wetted-area throat which is suitable for a simple wall-cooling arrangement. It can be incorporated in an engine pod or integrated with the airframe. A computer program written in FORTRAN IV language to determine the supersonic rotational flow field by the three-dimensional method of characteristics with the appropriate shock equations was used in designing the inlet. The computer program is written in two parts and is presented as an appendix. Data included are longitudinal static-pressure profiles throughout the inlet and subsonic diffuser, total-pressure recovery in the subsonic diffuser, and mass-flow ratios.

## SYMBOLS

$M_\infty$      free-stream Mach number

$w$      mass-flow rate, kilograms/second (measured by calibrated plug-venturi)

$w_\infty$      free-stream mass-flow rate in a cross-sectional area equal to frontal area of inlet lips, kilograms/second

$p$      static pressure, newtons/meter$^2$

$p_t$      total pressure, newtons/meter$^2$

$\overline{p_t}$      average total pressure, newtons/meter$^2$

$p_{t,\infty}$      free-stream total pressure, newtons/meter$^2$

$R$      radius, centimeters

$x$      distance from inlet lip, meters

$\gamma$      ratio of specific heats

$\eta_k$      kinetic-energy efficiency, $\quad 1 - \dfrac{\dfrac{2}{\gamma - 1}\left[\left(\dfrac{p_{t,\infty}}{p_t}\right)^{\frac{\gamma-1}{\gamma}} - 1\right]}{M_\infty^2}$

## APPARATUS AND MODELS

### Apparatus

The tests were run in the Langley 20-inch Mach 6 tunnel, which is described in reference 5. The free-stream total temperature is $455^\circ$ K ($820^\circ$ R) and the total pressure is 2655 kilonewtons per square meter. The test Reynolds number per meter is $24.58 \times 10^6$. The unit Reynolds number per meter at Mach 6 and 24 384 meters altitude is $5.5 \times 10^6$. Thus, an inlet 0.47 meter in diameter at 24 384 meters altitude would have a Reynolds number equivalent to the test Reynolds number. Photographs of the basic model are presented in figures 1 and 2, and a sketch is presented in figure 3(a). The model features all-internal compression, radiation cooling, boundary-layer bleed, and a subsonic diffuser having an area ratio of 3.22 and an equivalent half-angle of $3^\circ$. The aerodynamic design was chosen after a study of several possible inviscid designs was made. The supersonic diffuser is conical and has a half-angle of $9^\circ$. This design angle was chosen as a reasonable compromise between an isentropic inlet, which has excessive length coupled with ideal pressure recovery, and a steeper initial angle, which provides a desirable structural form but has poor aerodynamic characteristics. The estimated boundary-layer growth effectively increased the inviscid $9^\circ$ half-angle to $9.126^\circ$; this value was used as a basis for a final set of inviscid calculations. The inlet was designed by using a computer program written in FORTRAN IV language to compute the super-sonic rotational flow field by the three-dimensional method of characteristics. The FORTRAN program is an essential feature of the investigations, inasmuch as accurate and rapid calculations of such features as the curved shocks and the inviscid total-pressure recovery are not easily made by hand. Therefore, for the use of other investigators, the program is included herein as an appendix. The computer program indicates that the shock from the inlet lip intersects the model center line at station 14.72 centimeters, a point slightly upstream of the apex of a large notch in the flat side of the inlet. Starting the supersonic flow through the inlet is accomplished by opening a flap built into the flat lower surface of the model upstream of the boundary-layer bleed. Figure 2 is a photograph of the model with the starting flap opened.

The conical compression surface of the basic model is split to form a semicircular inlet and a flat plate is secured to the open side. The flat plate is notched in a symmetrical V-shape for a distance of 14.801 centimeters from the leading edge to provide an opening for radiation cooling of a large portion of the compression surface. (See fig. 1.) The notch does not affect the theoretical three-dimensional flow except at the apex, where the theoretical internal shock becomes a normal shock; a small amount of spillage is expected to occur at that point.

At station 20.927 centimeters, a boundary-layer-bleed scoop approximately 0.061 centimeter high surrounds the internal flow passage and the bleed air exits through the flat-plate side of the model. The Mach number at the edge of the boundary layer is estimated to be 3.10 at this station. Mass-flow integrations of the boundary-layer flow indicate that the bleed mass flow is 8.7 percent of the total mass flow.

The flow undergoes an additional conical compression downstream of the bleed station to the throat, where the Mach number is reduced to 2.95 and the total-pressure ratio is 0.727. The throat length is 5.31 times the initial throat radius and the throat expands at an equivalent conical half-angle of 0.5° to allow for boundary-layer growth. A normal (or terminal) shock at the throat should reduce the Mach number to 0.478 and the total-pressure ratio to 0.249.

The subsonic diffuser further reduces the Mach number to 0.115. At this low Mach number, the static pressure and the total pressure have almost the same value; 0.247 and 0.249 times the free-stream total pressure, respectively. The static-pressure rise is 113.31 times the free-stream static pressure. A transition from a semicircular to a circular duct is located in the duct downstream of the diffuser, and a combination plug-venturi is provided for mass-flow measurement and shock-position control.

Static pressures are measured at orifices located in a longitudinal row on the model from the inlet lip to the diffuser-measuring station. The diffuser is considered to be divided by concentric semicircles into 12 sections equal in area. One tube is placed in each of the 12 sections midway between the semicircles to measure the total-pressure recovery. A schlieren system is employed to determine visually when starting occurs and to see the flow disturbances occurring at the bleed flow exits.

The area distribution within the model is presented in figure 4. The capture area is 43.89 square centimeters and the length of the initial supersonic compression region (fig. 3(a)) is 20.927 centimeters, with a downstream area of 6.11 square centimeters at the boundary-layer-bleed station.

The minimum throat area is 4.19 square centimeters at station 26.327 centimeters; the area increases gradually to 4.77 square centimeters at station 35.334 centimeters. Downstream of this point, the area increases to 15.35 square centimeters in the subsonic

diffuser. There are no struts or steps in the internal flow passages other than the boundary-layer-bleed slot; changes in the slope of the area curve are all moderate.

## Models

A few preliminary runs of the basic configuration (fig. 3(a)) showed that the model throat was choked, that a shock was standing in the supersonic diffuser, and that air was spilling from the apex of the V-shaped notch. In order to increase the bleed mass flow and relieve the choking, the basic configuration was modified several different ways to make four new configurations.

The modifications which produced configuration I involved three changes of the basic configuration: the flap was shortened by 1.27 centimeters; the approach to the boundary-layer-bleed slot was cut away at a 15° angle starting at station 19.812 centimeters; and the size of the bleed exits was doubled and two new bleed exits 2.54 centimeters long were made adjacent to the opening at the flap trailing edge. A sketch of configuration I is shown in figure 3(b).

Configuration II was formed by rounding the approach to the boundary-layer-bleed slot to a radius of 5.08 millimeters and thus reducing the effective size of the bleed flow slot. This modification, which was accomplished by placing a new insert at the entrance to the bleed slot, was made in an attempt to decrease the strength of the expansion entering the throat. At the same time, the downstream edge of the boundary-layer-bleed slot was notched to break up any shock concentrations within the throat. This configuration is shown in figure 3(c).

Two additional modifications were made to reduce the boundary-layer thickness and the extension of the normal shock into the subsonic diffuser. The bleed exits were further enlarged by cutting them 1.91 centimeters farther forward and perforating the throat with 10 holes 1.59 millimeters in diameter. A sketch of this model, designated configuration III, is shown in figure 3(d).

Configuration IV was made by closing the throat bleed holes and doubling the size of the serrations at the downstream edge of the boundary-layer-bleed slot. A sketch is shown in figure 3(e).

The semicircular model used in the present investigation is not suitable for simple variable-geometry configurations. Therefore, the tests were made with all the component parts except the starting flap and the exit plug in a fixed position.

# RESULTS AND DISCUSSION

## Static-Pressure Distributions

The theoretical static-pressure distribution is presented in figure 5(a), and the modified experimental pressure distributions for configuration I are presented in figure 5(b). Each curve represents a different setting of the area at the plug-venturi. Upstream of the bleed station, the predicted and measured pressures are in good agreement. Downstream of the bleed station, however, the measured pressures indicate a pressure drop which probably originates as an expansion on the cutaway portion of the flap and the cutaway approach to the boundary-layer-bleed slot. This expansion results in high Mach numbers and, consequently, in large reductions of total pressure in the terminal shock that follows. This condition should be avoided whenever possible by using scoops rather than flush slots for boundary-layer removal. The terminal-shock pressure rise is distributed throughout the throat and much of the subsonic diffuser rather than concentrated in the throat as it should be for maximum recovery. The terminal shock is followed by subsonic compression to the station at which the total pressure is measured. At the condition at which the static-pressure rise is a maximum, the bleed mass-flow rate is 13.3 percent of the capture mass flow. The values of the average total pressure measured at the end of the subsonic diffuser and the mass-flow ratio as measured by the plug-venturi are shown in the right-hand margin of the figure. In each case for comparison, the average-total-pressure ratio is also plotted by using the same symbol that was used for the corresponding static-pressure-ratio curve. Static-pressure measurements for configuration II are presented in figure 5(c). The results are similar to those shown in figure 5(b).

Static-pressure measurements for configuration III are presented in figure 5(d). The static-pressure distributions reveal the strong expansion immediately downstream of the boundary-layer-bleed slot noted previously in figures 5(b) and 5(c) and terminal-shock and subsonic-diffuser characteristics similar to those of figures 5(b) and 5(c). The maximum static pressure is about 1 percent of $p_{t,\infty}$ greater than the level obtained for any previous test condition. This maximum pressure occurs when the terminal shock originates in the converging duct upstream of the throat. Stable operation at this condition suggests that most of the boundary layer has been removed by the enlarged bleed exits. The bleed flow rate, defined by $1 - \frac{w}{w_\infty}$, is 2.7 percent greater at the point of maximum total-pressure recovery than the corresponding rate for configuration II.

Static-pressure distributions for configuration IV are presented in figure 5(e). The expansion downstream of the boundary-layer bleed is still apparent, but a distributed pressure rise occurs in the throat region for all flow conditions. The terminal shock is still extended downstream into the subsonic diffuser, but the maximum diffuser static

pressure has increased to 0.183 times the free-stream total pressure and the corresponding bleed mass-flow rate is 4.4 percent below the rate for configuration III. The terminal shock for maximum total-pressure recovery starts slightly upstream of the throat section but appears to be quite stable in this configuration. This stability indicates that the boundary layer has been effectively removed.

## Total-Pressure Ratios

Total-pressure-ratio distributions within the constant-area duct downstream of the subsonic diffuser are presented in figure 6. Lines of constant-total-pressure ratio are mapped at intervals of 0.0010. The more constant-total-pressure distributions occur for the critical and subcritical operating conditions (i.e., the terminal shock at the throat or upstream of the throat, respectively), while large total-pressure gradients exist for extreme supercritical operating conditions (i.e., terminal shock downstream of the throat). These large total-pressure gradients resulted because the normal shock was in a region of high velocities where thick boundary layers with lambda-type shocks would be likely to exist. These shocks extend into the constant-area duct downstream of the subsonic diffuser. The results of this shock extension may be seen in the static-pressure distributions presented in figure 5.

The variation of total-pressure ratio with mass-flow ratio is presented in figure 7. These data are similar for all four configurations in that none of them have any useful subcritical flow regions for the normal, closed-flap mode of operation. This characteristic is typical of internal-compression inlets. Configuration IV with large serrations on the downstream side of the bleed flow slots provides the peak total-pressure recovery of 0.187 (design value is 0.249) at a value of the mass-flow ratio of 0.887. This mass-flow ratio corresponds to a bleed mass-flow rate of 11.3 percent, which is 2.6 percent larger than the design value of 8.7 percent because of the enlarged bleed flow entrance and exit areas. Although the total-pressure recovery and mass-flow ratio drop sharply for subcritical operation with the flap closed, opening the flap slightly permits excess mass flow to bypass the throat and the dashed-line portion of the curve results. Opening the flap improves the total-pressure recovery because the position of the normal shock can be located in the region near the boundary-layer-bleed slot rather than the higher Mach number region near the apex of the V-shaped notch. The results obtained from configuration IV indicate that the mass-flow rate may be reduced to a level of about 60 percent, while the total-pressure ratio is reduced only about 1.5 percent. Similar stable subcritical-mass-flow operation is reported in reference 6 for a fixed-geometry asymmetric inlet operating at Mach number 3.85. The inlet of reference 6 at several angles of attack also provided mass-flow and pressure-recovery performance characteristics superior to those of axially symmetric inlets. It is believed that the inlet of the

present investigation would have similar performance characteristics at a nonzero angle of attack because both inlets have increasing frontal areas as the angle of attack is increased.

Although the inlet of the present investigation was designed with a subsonic diffuser, similar inlets may be used to supply air to supersonic combustion ramjets. Surveys were attempted at the throat to determine the recovery and to compare the experimental and theoretical flow conditions. In every attempt, the rake choked the throat and endeavors to start the flow destroyed the rake. Despite these discouraging results, the excellent correlation of static pressures in the supersonic diffuser indicates that the flow up to the throat behaved as theoretically predicted. The distributed static-pressure rise in the subsonic diffuser probably is a primary cause of the discrepancy between predicted and experimental total pressures. Thus, this type of inlet would probably be satisfactory for supplying air to a supersonic combustion ramjet.

## Kinetic-Energy Efficiency

The pressure recovery data of figure 7 are presented in figure 8 in the form of the variation of kinetic-energy efficiency with mass-flow ratio. The maximum value of $\eta_k$ is 0.915. This value is 0.017 less than the design value of 0.932. Reducing the mass flow by opening the flap and spilling 30 percent of the flow reduces the value of $\eta_k$ to 0.909, a reduction of only 0.006. These experimental values of kinetic-energy efficiency are considered to be within the range of interest for practical engine applications.

Design-point recoveries and efficiencies were not obtained because expansion waves generated at the boundary-layer-bleed slot increased the local Mach numbers and shock losses at the throat.

## SUMMARY OF RESULTS

An investigation of a semicircular all-internal-compression inlet has been made at a Mach number of 6. The inlet was designed by using a computer program written in FORTRAN language; the program employed the three-dimensional method of characteristics. The investigation indicated the following results:

1. The experimental pressures in the supersonic diffuser were in good agreement with those predicted by the method of characteristics.

2. The terminal shock was distributed throughout the throat region and much of the subsonic diffuser.

3. The terminal shock originated in the converging duct upstream of the throat. The stability of this flow structure indicated that the boundary layer had been effectively removed.

4. The maximum total-pressure recovery of 0.187, which was 0.062 less than the design value of 0.249, occurred with a boundary-layer bleed mass-flow rate of 11.3 percent.

5. Subcritical mass-flow rates of 60 percent were achieved with a decrease of only 1.5 percent in total-pressure recovery.

6. The maximum value of kinetic-energy efficiency was 0.915, a value which was 0.017 less than the design value. This value is considered to be in the range of interest for practical engine applications.

Langley Research Center,
National Aeronautics and Space Administration,
Langley Station, Hampton, Va., November 30, 1965.

# APPENDIX

## PROGRAM FOR SUPERSONIC DIFFUSER FLOW FIELD

A computer program has been written in FORTRAN IV language (ref. 7) in two parts to determine the flow field within the supersonic diffuser. The three-dimensional method of characteristics with the appropriate shock equations is used. The application of the method of characteristics to supersonic rotational flow is described in reference 8. The upstream flow field is assumed to be uniform with no Mach number or pressure gradients and the direction of flow is assumed to be parallel to the body axis of symmetry.

The first part of the program defines the initial shock and the flow field between the initial shock and the reflected shock, as shown in figure A-1. The input data required are the Mach number, the entropy, the equation defining the wall, the flow deflection angle on the shock, and the flow deflection angle on the wall. Calculations are made at the leading edge and along characteristic lines starting at the shock and going upward to the right until they reach the wall. As the flow field becomes filled and the shock approaches the center line, characteristic lines of the same family begin to cross each other at some distance from the shock. The data obtained in this region, of course, are not usable, but the calculations are made in the region near the shock until a subsonic Mach number downstream of the shock is reached. If the shock is too steep, subsonic flow may exist at large radial distances from the center line and the approximation for the second part of the program will not be accurate. For the present case, subsonic flow exists only within a radius of 0.0077 times the lip radius and thus affects only 0.0059 percent of the mass flow. Therefore, the effect is considered negligible for these calculations.



(a) Initial shock and flow region which follows.



(b) Reflected shock and flow region which follows.

Figure A-1.- Sketch of initial and reflected shocks and associated flow regions.

The second part of the program defines the reflected shock and the supersonic flow field which follows. The position of the reflected shock is first estimated as follows:

1. The first point of the reflected shock is assumed to be the last computed point (nearest the center line) of the initial shock.

2. The flow direction downstream of the reflected shock is assumed to be parallel to the center line.

3. The flow at the center line ahead of the reflected shock is assumed to be at the same Mach number, static pressure, and total pressure as the flow at the last computed point of the initial shock. The region of subsonic flow at the center line downstream of the initial shock is ignored.

The path of the reflected shock is estimated on the basis of these assumptions, and equations are written for the variation of local Mach number M, flow angle $\theta$, and entropy S with distance from the center line. A term is included in these equations to correct for slight upstream or downstream deviations of the reflected shock from the predicted path. The equations used in subroutine subr are as follows:

$$M = 2.685947 + 0.725327Y + \left(-17.506468Y^2 + 7.870908Y - 0.152477\right)^{1/2}$$

$$- (1.6 - 2.857Y) \frac{X - (Y + 0.7479)}{0.277}$$

$$\theta_{radians} = \frac{-0.0325}{Y^{0.6475}} - 1.65Y^{2.795} + 0.0424 \frac{\frac{X - (Y + 0.7479)}{0.277}}{Y^{1.068}}$$

$$S = \frac{153}{Y^{0.675}}$$

where X is the distance downstream of the inlet lip and Y is the radius expressed in terms of the lip radius. Calculations are made at the intersection of the initial shock and the center line and along characteristic lines starting at the reflected shock and going downward to the right until they reach the center line. The calculations are continued until characteristic lines intersect the center line at a given distance downstream of the shock.

The printout data of the first part of the program included the following parameters for each point calculated in the flow field:

X          distance downstream of inlet lip, expressed in terms of lip radius

Y          radius to point, expressed in terms of lip radius

$\theta$          flow angle, degrees

M          local Mach number

W          ratio of local to limiting velocity

$$S = R \log_e\left(\frac{p_{t,1}}{p_t}\right) \quad \text{(where } R \text{ is the gas constant)}$$

$\dfrac{p}{p_1}$          ratio of local static to free-stream static pressure

$\dfrac{p - p_1}{q_1}$          static-pressure rise divided by free-stream dynamic pressure

The printout data of the second part of the program differ from those of the first part in that total-pressure and mass-flow parameters are included and static-pressure ratios are omitted. This change is made to facilitate a mass-weighted integration of the flow field at the station where the reflected shock intersects the inlet wall. The total-pressure and mass-flow parameters are as follows:

$\dfrac{p_t}{p_{t,1}}$          ratio of local total pressure to free-stream total pressure

$\left(\dfrac{p_t}{p_{t,1}}\right)M\left(1 - W^2\right)^3$          parameter used to determine mass-flow rate

$\left(\dfrac{p_t}{p_{t,1}}\right)^2 M\left(1 - W^2\right)^3$          parameter used to determine mass-weighted total-pressure ratio

The computer program for the IBM 7094 electronic data processing system with typical input data follows.

# APPENDIX

```
        SAMPLE INPUT TO INITIAL SHOCK REGION
$DATA
J1=0,J2=9999.,J3=1.4,J4=1716.,J5=1.,J6=-.1606395,J7=6.,J8=0,J9=1.,,
J10=.035,J11=.9943776,J12=4.7645,J13=-9.1260145,J14=293.013,
J15=-16.759818,J16=1.$
        WHERE
        J1     Y LIMIT ON SHOCK
               TYPICALLY=0 TO STOP CALCULATION WHEN INITIAL SHOCK
               REACHES THE CENTERLINE
        J2     X LIMIT ON WALL
               TYPICALLY=9999. TO ALLOW Y LIMIT TO STOP THE CALCULATION
        J3     GAMMA
               TYPICALLY=1.4 FOR AIR
        J4     R GAS CONSTANT
               TYPICALLY=1716. FOR AIR
        J5     B WHERE Y=AX+B IS EQUATION DEFINING WALL
               TYPICALLY=1.
        J6     A WHERE Y=AX+B IS EQUATION DEFINING WALL
               TYPICALLY=-.1606395
        J7     MACH NUMBER AHEAD OF INITIAL SHOCK
               TYPICALLY=6.
        J8     XB COORDINATE OF FIRST POINT ON WALL AND INITIAL SHOCK
               TYPICALLY=0
        J9     YB COORDINATE OF FIRST POINT ON WALL AND INITIAL SHOCK
               TYPICALLY=1.
        J10    XA COORDINATE OF SECOND POINT ON WALL
               TYPICALLY=.035
        J11    YA COORDINATE OF SECOND POINT ON WALL
               TYPICALLY=.9943776
        J12    MACH NUMBER AT FIRST AND SECOND POINTS
               TYPICALLY=4.7645
        J13    FLOW DEFLECTION ANGLE AT FIRST AND SECOND POINTS--NEGATIVE
               ANGLE DEGREES
               TYPICALLY=-9.1260145
        J14    ENTROPY AT FIRST AND SECOND POINTS
               TYPICALLY=293.013
        J15    SHOCK ANGLE AT FIRST POINT--NEGATIVE ANGLE DEGREES
               TYPICALLY=-16.759818
        J16    +1. TO PRINT ALL POINTS,OR =0 TO PRINT ONLY WALL AND
               SHOCK POINTS
               TYPICALLY=1.
        $      INDICATES END OF INPUT DATA
```

# APPENDIX

SUBROUTINE BODYX COMPUTES THE WALL EQUATION Y=AX+B.
A NEW SUBROUTINE WILL BE NEEDED IF THE EQUATION OF THE
WALL IS CHANGED.
SAMPLE INPUT TO REFLECTED SHOCK REGION

```
$DATA
J1=9999.,J2=5.,J3=1.4,J4=1716.,J8=2.785644,J9=.022561,J10=2.785644,
J11=0,J12=1.1338618,J13=0,J14=3711.433,J15=29.610459,J16=1.$
```

        WHERE
        J1      Y LIMIT ON SHOCK
                TYPICALLY=9999. TO ALLOW X LIMIT TO STOP THE CALCULATION
        J2      X LIMIT ON CENTERLINE
                TYPICALLY=5.
        J3      GAMMA
                TYPICALLY=1.4 FOR AIR
        J4      R GAS CONSTANT
                TYPICALLY=1716. FOR AIR
        J5      NOT USED ON REFLECTED SHOCK

        J6      NOT USED ON REFLECTED SHOCK

        J7      NOT USED ON REFLECTED SHOCK

        J8      XB COORDINATE OF FIRST POINT ON REFLECTED SHOCK
                TYPICALLY=2.785644=LAST COMPUTED POINT OF INITIAL SHOCK
        J9      YB COORDINATE OF FIRST POINT ON REFLECTED SHOCK
                TYPICALLY=.022561
        J10     XA COORDINATE OF CENTERLINE POINT
                TYPICALLY=2.785644
        J11     YA COORDINATE OF CENTERLINE POINT
                TYPICALLY=0
        J12     MACH NUMBER AT FIRST POINT ON REFLECTED SHOCK AND
                CENTERLINE POINT
                TYPICALLY=1.1338618
        J13     FLOW DEFLECTION ANGLE AT FIRST POINT ON REFLECTED SHOCK
                AND CENTERLINE POINT
                TYPICALLY=0
        J14     ENTROPY AT FIRST POINT ON REFLECTED SHOCK AND
                CENTERLINE POINT
                TYPICALLY=3711.433
        J15     SHOCK ANGLE AT FIRST POINT ON REFLECTED SHOCK
                --POSITIVE ANGLE DEGREES
                TYPICALLY=29.610459
        J16     +1. TO PRINT ALL POINTS,OR =0 TO PRINT ONLY
                CENTERLINE AND SHOCK POINT
                TYPICALLY=1.

14

# APPENDIX

```
$       INDICATES END OF INPUT DATA
SUBROUTINE SUBR COMPUTES ENEWM,THC1,SC1 AS FUNCTIONS OF
XC AND YC. THESE ARE THE EQUATIONS FOR M,-THETA,S
AHEAD OF THE REFLECTED SHOCK. A NEW SUBROUTINE
WILL BE NEEDED IF EQUATIONS ARE CHANGED.
```

# APPENDIX

```
$IBFTC MAIN      REF
C       MAINPROGRAM-FIRSTSHOCKREGION
        COMMONXA,YA,THA,WA,SMUA,CMUA,STHA,CTHA,SA,XB,YB,THB,
       1WB,SMUB,CMUB,STHB,CTHB,SB,EPB,TEPB,XC,YC,THC,WC,
       2SMUC,CMUC,STHC,CTHC,SC,EPC,TEPC,EMUA,EMUB,EMUC,THAC,
       3WAC,SMUAC,YAC,EMUAC,STHAC,ELAC,THBC,WBC,SMUBC,YBC,EMUBC,
       4STHBC,EPBC,TEPBC,EMBC,TANMA,TANMB,EMC,PC,CPC,EM,THCP,
       5COS1,TAN1,COS2,TAN2,KOUNT,TAPE,ALIGHT,BEGS,SVCON,SVCON1,
       6SVCON2,SVCON3,SVCON4,SVCON5,SVCON6,SVCON7,SVCON8,SVCON9,SVCO10,
       7SVCO11,  EEP,EEP1,EEP2,EEP3,EEP4,EEP5,EEP6,EEP7,CNTRL,CNTRL1,
       8CNTRL2,CNTRL3,CNTRL4,CNTRL5,CNTRL6,KNTRL7,CNTRL8,CNTRL9,CNTR10,
       9KNTR11,CNTR12,CNTR13,CNTR14,CNTR15,CNTR16,CNTR17,CNTR18,CNTR19,
       XCNTR54,ERASE,ERAS1,ERAS2,ERAS3,ERAS4,ERAS5,ERAS6,ERAS7,
       XERAS8,ERAS9,ERAS10,ERAS11,ERAS12,ERAS13,ERAS14,ERAS15,ERAS16
        COMMONERAS17,ERAS18,ERAS19,ERAS20,ERAS21,ERAS22,ERAS23,
       1ERAS24,ERAS25,ERAS26,ERAS27,ERAS28,ERAS29,ERAS30,ERAS31,
       2ERAS32,ERAS33,ERAS34,ERAS35,DEC,DEC1,DEC2,DEC3,DEC4,
       3DEC5,DEC6,DEC7,DEC8,DEC9,DEC10,DEC11,KON,CON1,PRT,
       4PRT1,PRT2,PRT3,PRT4,PRT5,PRT6,PRT7,PRT8,PRT9,DEG,
       5TEMP,TEMP1,TEMP2,TEMP3,TEMP4,XI,YI,THI,WI,SMUI,
       6CMUI,STHI,CTHI,SI,KER10,EX1,EX2,C1,C2,C3,C4,C5,C6,
       7C7,C8,C9,C10,C11,C12,C13,C14,C15,C16,C17,C18,C19,C20,
       8C21,C22,C23,C24,C25,C26,C27,C28,C29,C30,SAV,SAV1,
       9SAV2,SAV3,SAV4,SAV5,SAV6,SAV7,SAV8,SAV9,SC1,THCPR,ENEWST,
       XENEWCT,EKP,EKP1,EKP2,EKP3,EKP4,EKP5,ENEWTH,THC1,ENEWM,
       XAA,KAC,NRET,SW2,EN(9),PRNOPT,HOLD,J,K,L,STOR(1000)
        COMMON LTEST,BSHK1
        TAPE=2.
        ALIGHT=0
        DEC=0
        DEC1=1.
        DEC2=2.
        DEC3=1.570796327
        DEC4=6.283185308
        DEC5=0
        DEC6=0
        DEC7=7
        DEC8=0
        DEC9=9
        DEC10=0
        DEC11=11
        KON=1
        CON1=3.
        DEG=57.2957795
      9 CALLSLITE(0)
```

```
      WRITE(6,98)
98    FORMAT(1H1,1HX,15X,1HY,15X,9HTHETA DEG,7X,1HM,15X,1HW,15X,1HS,15X,
     14HP/PI,12X,9H(P-PI)/QI)
      DO 999 NN=1,1000
999   STOR(NN)=0
      HOLD=1.
      J=1
      K=1
      L=1
      CALL SLITE(2)
      KER10=0
      CALL FINP(16,CNTRL,CNTRL1,CNTRL3,CNTRL5,CNTR15,CNTR16,EM1,XB,YB,
     1XA,YA,EMB,THB,SB,EPB,PRNOPT)
      EPB=EPB/DEG
      THB=THB/DEG
      CNTRL6=9999.
      KNTRL7=3
      CNTRL8=1.
      CNTRL9=1.
      KNTR11=0
      EEP5=EM1*EM1
      EEP1=EEP5+EEP5
      EEP4=EEP1+DEC1
      EEP=EEP5*EEP5
      EEP3=((CNTRL3+DEC1)/DEC2)*EEP5+DEC1
      EEP1=-EEP3*EEP1
      EEP2=-(EEP5+DEC2)*EEP5
      SW2=0
      WB=SQRT(DEC1/(DEC1+DEC2/((CNTRL3-DEC1)*EMB*EMB)))
      SMUB=DEC1/EMB
      SMUA=SMUB
      CMUB=SQRT(1.-SMUB*SMUB)
      CMUA=CMUB
      STHB=SIN(THB)
      CTHB=COS(THB)
      STHA=STHB
      CTHA=CTHB
      SA=SB
      WA=WB
      THA=THB
      TEPB=SIN(EPB)/COS(EPB)
      BEGS=EPB
      BSHK1=0
```

17

```
      CALLSHKPT
      CALLPRINT
      CALLWRTSK
      BSHK1=1.
      CALLMOVCB
      CALLMOVAC
      CALLMOVBA
      CALLIPT
      GOTO(22,22,22,22,22,23),NRET
   22 CALLMOVCS
      CALLMOVIC
      CALLWRTGN
      CALLPRINT
      CALLMOVSC
   23 CALLWRTGN
      CALLPRINT
      CALLSPACE
      CALLWRTFL
      CALLRDS
      GOTO(10,11),NRET
   10 CALLEXIT
   11 CALLRDA
      GOTO(12,13),NRET
   12 CALLEXIT
   13 CALLSHKPT
      CALLPRINT
      CALLWRTSK
      CALLMOVCA
      CALLRDB2
      GOTO(14,15),NRET
   14 CALLEXIT
   15 CALLGEN
      CALLIPT
      GOTO(24,24,24,24,24,25),NRET
   24 CALLMOVBA
      CALLMOVCB
      CALLMOVIC
      CALLWRTGN
      GOTO7757
   25 CALLMOVBA
      CALLMOVCB
   28 CALLWRTGN
      CALLPRINT
      CALLBODY
      CALLWRTGN
```

```
      CALLPRINT
      CALLSPACE
      CALLWRTFL
   7  CALLRDB
      GOTO(16,17),NRET
  16  CALLEXIT
  17  CALLRDA
      GOTO(18,19),NRET
  18  CALLEXIT
  19  CALLSHKPT
      CALLPRINT
      CALLWRTSK
      IF(YC-CNTRL)5,30,30
  30  CALLMOVCA
      CALLRDB2
      GOTO(20,21),NRET
  20  CALLEXIT
  21  CALLGEN
      CALLIPT
      GOTO(26,26,26,26,26,27),NRET
  26  CALLMOVCA
      CALLMOVIC
      CALLWRTGN
      CALLPRINT
      CALLMOVAC
  27  CALLWRTGN
      CALLPRINT
   4  CALLMOVCA
      CALLRDB2
      GO TO (31,32),NRET
31    GOTO1
32    CALLGEN
      IF(DEC)3610,34,3610
34    CALL WRTGN
      IF(PRNOPT)3,2,3
3     CALL PRINT
2     GO TO 4
   1  CALLMOVBA
      CALLMOVCB
      CALLBODY
      CALLWRTGN
      CALLPRINT
3610  DEC=0
```

```
      CALLWRTFL
      CALLSPACE
      IF(XC-CNTRL1)6,6,5
   6  IF(SW2)8,7,8
   8  WRITE(6,100)TAPE,ALIGHT
   5  GOTO9
7757  CALLPRINT
      CALLMOVBC
      GOTO28
 100  FORMAT(2E16.8)
      END
$IBFTC EPSR     REF
      SUBROUTINEEPSR
      COMMONXA,YA,THA,WA,SMUA,CMUA,STHA,CTHA,SA,XB,YB,THB,
     1WB,SMUB,CMUB,STHB,CTHB,SB,EPB,TEPB,XC,YC,THC,WC,
     2SMUC,CMUC,STHC,CTHC,SC,EPC,TEPC,EMUA,EMUB,EMUC,THAC,
     3WAC,SMUAC,YAC,EMUAC,STHAC,ELAC,THBC,WBC,SMUBC,YBC,EMUBC,
     4STHBC,EPBC,TEPBC,EMBC,TANMA,TANMB,EMC,PC,CPC,EM,THCP,
     5COS1,TAN1,COS2,TAN2,KOUNT,TAPE,ALIGHT,BEGS,SVCON,SVCON1,
     6SVCON2,SVCON3,SVCON4,SVCON5,SVCON6,SVCON7,SVCON8,SVCON9,SVCO10,
     7SVCO11, EEP,EEP1,EEP2,EEP3,EEP4,EEP5,EEP6,EEP7,CNTRL,CNTRL1,
     8CNTRL2,CNTRL3,CNTRL4,CNTRL5,CNTRL6,KNTRL7,CNTRL8,CNTRL9,CNTR10,
     9KNTR11,CNTR12,CNTR13,CNTR14,CNTR15,CNTR16,CNTR17,CNTR18,CNTR19,
     XCNTR54,ERASE,ERAS1,ERAS2,ERAS3,ERAS4,ERAS5,ERAS6,ERAS7,
     XERAS8,ERAS9,ERAS10,ERAS11,ERAS12,ERAS13,ERAS14,ERAS15,ERAS16
      COMMONERAS17,ERAS18,ERAS19,ERAS20,ERAS21,ERAS22,ERAS23,
     1ERAS24,ERAS25,ERAS26,ERAS27,ERAS28,ERAS29,ERAS30,ERAS31,
     2ERAS32,ERAS33,ERAS34,ERAS35,DEC,DEC1,DEC2,DEC3,DEC4,
     3DEC5,DEC6,DEC7,DEC8,DEC9,DEC10,DEC11,KON,CON1,PRT,
     4PRT1,PRT2,PRT3,PRT4,PRT5,PRT6,PRT7,PRT8,PRT9,DEG,
     5TEMP,TEMP1,TEMP2,TEMP3,TEMP4,XI,YI,THI,WI,SMUI,
     6CMUI,STHI,CTHI,SI,KER10,EX1,EX2,C1,C2,C3,C4,C5,C6,
     7C7,C8,C9,C10,C11,C12,C13,C14,C15,C16,C17,C18,C19,C20,
     8C21,C22,C23,C24,C25,C26,C27,C28,C29,C30,SAV,SAV1,
     9SAV2,SAV3,SAV4,SAV5,SAV6,SAV7,SAV8,SAV9,SC1,THCPR,ENEWST,
     XENEWCT,EKP,EKP1,EKP2,EKP3,EKP4,EKP5,ENEWTH,THC1,ENEWM,
     XAA,KAC,NRET,SW2,EN(9),PRNOPT,HOLD,J,K,L,STOR(1000)
      ERASE=ERASE*ERASE
      ERAS1=ERASE*EEP+EEP
      ERAS2=(ERASE*EEP1+EEP2)/CON1
      ERAS13=(EEP3*EEP3*ERASE+EEP4)/CON1
      ERAS6=ERAS13*ERAS2+ERAS1
      ERAS9=ERAS2*ERAS2
      ERAS15=ERAS1*ERAS13-ERAS9
      ERASE=ERAS15+ERAS15
```

```
      ERAS10=(ERAS6/ERASE)*ERAS1+ERAS2
      ERAS6=ERAS6*ERAS6
      ERAS7=ERAS13*ERAS13+ERAS2
      AA=(SQRT(ABS((ERAS7+ERAS7)*ERASE+ERAS6))/ERASE)*ERAS1
      AA=ATAN2(AA,ERAS10)
      IF(AA)2,2,1
    2 AA=AA+DEC4
    1 ERASE=AA/CON1
      ERASE=COS(ERASE)
      ERAS9=SQRT(-ERAS15)
      ERASE=-((ERAS9+ERAS9)*ERASE+ERAS2)/ERAS1
      ERAS2=SQRT(DEC1-ERASE)
      ERAS1=-SQRT(ERASE)
      TEPC=ERAS1/ERAS2
      EPC=ATAN(TEPC)
      RETURN
      END
$IBFTC BODY     REF
      SUBROUTINEBODY
      COMMONXA,YA,THA,WA,SMUA,CMUA,STHA,CTHA,SA,XB,YB,THB,
     1WB,SMUB,CMUB,STHB,CTHB,SB,EPB,TEPB,XC,YC,THC,WC,
     2SMUC,CMUC,STHC,CTHC,SC,EPC,TEPC,EMUA,EMUB,EMUC,THAC,
     3WAC,SMUAC,YAC,EMUAC,STHAC,ELAC,THBC,WBC,SMUBC,YBC,EMUBC,
     4STHBC,EPBC,TEPBC,EMBC,TANMA,TANMB,EMC,PC,CPC,EM,THCP,
     5COS1,TAN1,COS2,TAN2,KOUNT,TAPE,ALIGHT,BEGS,SVCON,SVCON1,
     6SVCON2,SVCON3,SVCON4,SVCON5,SVCON6,SVCON7,SVCON8,SVCON9,SVCO10,
     7SVCO11, EEP,EEP1,EEP2,EEP3,EEP4,EEP5,EEP6,EEP7,CNTRL,CNTRL1,
     8CNTRL2,CNTRL3,CNTRL4,CNTRL5,CNTRL6,KNTRL7,CNTRL8,CNTRL9,CNTR10,
     9KNTR11,CNTR12,CNTR13,CNTR14,CNTR15,CNTR16,CNTR17,CNTR18,CNTR19,
     XCNTR54,ERASE,ERAS1,ERAS2,ERAS3,ERAS4,ERAS5,ERAS6,ERAS7,
     XERAS8,ERAS9,ERAS10,ERAS11,ERAS12,ERAS13,ERAS14,ERAS15,ERAS16
      COMMONERAS17,ERAS18,ERAS19,ERAS20,ERAS21,ERAS22,ERAS23,
     1ERAS24,ERAS25,ERAS26,ERAS27,ERAS28,ERAS29,ERAS30,ERAS31,
     2ERAS32,ERAS33,ERAS34,ERAS35,DEC,DEC1,DEC2,DEC3,DEC4,
     3DEC5,DEC6,DEC7,DEC8,DEC9,DEC10,DEC11,KON,CON1,PRT,
     4PRT1,PRT2,PRT3,PRT4,PRT5,PRT6,PRT7,PRT8,PRT9,DEG,
     5TEMP,TEMP1,TEMP2,TEMP3,TEMP4,XI,YI,THI,WI,SMUI,
     6CMUI,STHI,CTHI,SI,KER10,EX1,EX2,C1,C2,C3,C4,C5,C6,
     7C7,C8,C9,C10,C11,C12,C13,C14,C15,C16,C17,C18,C19,C20,
     8C21,C22,C23,C24,C25,C26,C27,C28,C29,C30,SAV,SAV1,
     9SAV2,SAV3,SAV4,SAV5,SAV6,SAV7,SAV8,SAV9,SC1,THCPR,ENEWST,
     XENEWCT,EKP,EKP1,EKP2,EKP3,EKP4,EKP5,ENEWTH,THC1,ENEWM,
     XAA,KAC,NRET,SW2,EN(9),PRNOPT,HOLD,J,K,L,STOR(1000)
```

```
      COMMON LTEST
      WBC=WB
      KOUNT=0
      ERAS2=SMUB/CMUB
      EMUB=ATAN(ERAS2)
      SC=SA
   9  THCP=THC,
      CALLBODYX
      IF(CNTRL8)2,1,2
   2  ERASE=CTHB*CMUB
      ERAS1=STHB*SMUB
      ERASE=-ERAS1+ERASE
      ERAS2=SMUB/CMUB
      ERASE=(ERAS2*ERAS1)/ERASE
      YBC=(YB+YC)/DEC2
      ERASE=((XC-XB)/YBC)*ERASE
      GOTO3
   1  ERASE=0
   3  CALLSLITET(2,LTEST)
      GOTO(5,4),LTEST
   5  CALLSLITE(2)
      GOTO6
   4  AA=0
      GOTO7
   6  IF(CNTRL9)8,7,8
   8  AA=(((((SC-SB)/CNTRL3)*SMUB)/CNTRL5)*SMUB
   7  ERASE=AA-ERASE
      WC=(-(THB-THC)*ERAS2-ERASE)*WBC+WB
      CALLMUSR
      IF(DEC)21,20,21
  20    EMUB=(EMUC+EMUB)/DEC2
        SMUB=SIN(EMUB)
        CMUB=COS(EMUB)
        THBC=(THB+THC)/DEC2
        STHB=SIN(THBC)
        CTHB=COS(THBC)
        WBC=(WB+WC)/DEC2
        KOUNT=(KOUNT+KON)
        IF(KOUNT-KNTRL7)9,10,10
  10  IF(ABS(THC-THCP)-CNTRL6)11,11,9
  11  STHC=SIN(THC)
      CTHC=COS(THC)
  21    RETURN
        END
$IBFTC THASR    REF
```

# APPENDIX

```
SUBROUTINETHASR
 COMMONXA,YA,THA,WA,SMUA,CMUA,STHA,CTHA,SA,XB,YB,THB,
1WB,SMUB,CMUB,STHB,CTHB,SB,EPB,TEPB,XC,YC,THC,WC,
2SMUC,CMUC,STHC,CTHC,SC,EPC,TEPC,EMUA,EMUB,EMUC,THAC,
3WAC,SMUAC,YAC,EMUAC,STHAC,ELAC,THBC,WBC,SMUBC,YBC,EMUBC,
4STHBC,EPBC,TEPBC,EMBC,TANMA,TANMB,EMC,PC,CPC,EM,THCP,
5COS1,TAN1,COS2,TAN2,KOUNT,TAPE,ALIGHT,BEGS,SVCON,SVCON1,
6SVCON2,SVCON3,SVCON4,SVCON5,SVCON6,SVCON7,SVCON8,SVCON9,SVCO10,
7SVCO11, EEP,EEP1,EEP2,EEP3,EEP4,EEP5,EEP6,EEP7,CNTRL,CNTRL1,
8CNTRL2,CNTRL3,CNTRL4,CNTRL5,CNTRL6,KNTRL7,CNTRL8,CNTRL9,CNTR10,
9KNTR11,CNTR12,CNTR13,CNTR14,CNTR15,CNTR16,CNTR17,CNTR18,CNTR19,
XCNTR54,ERASE,ERAS1,ERAS2,ERAS3,ERAS4,ERAS5,ERAS6,ERAS7,
XERAS8,ERAS9,ERAS10,ERAS11,ERAS12,ERAS13,ERAS14,ERAS15,ERAS16
 COMMONERAS17,ERAS18,ERAS19,ERAS20,ERAS21,ERAS22,ERAS23,
1ERAS24,ERAS25,ERAS26,ERAS27,ERAS28,ERAS29,ERAS30,ERAS31,
2ERAS32,ERAS33,ERAS34,ERAS35,DEC,DEC1,DEC2,DEC3,DEC4,
3DEC5,DEC6,DEC7,DEC8,DEC9,DEC10,DEC11,KON,CON1,PRT,
4PRT1,PRT2,PRT3,PRT4,PRT5,PRT6,PRT7,PRT8,PRT9,DEG,
5TEMP,TEMP1,TEMP2,TEMP3,TEMP4,XI,YI,THI,WI,SMUI,
6CMUI,STHI,CTHI,SI,KER10,EX1,EX2,C1,C2,C3,C4,C5,C6,
7C7,C8,C9,C10,C11,C12,C13,C14,C15,C16,C17,C18,C19,C20,
8C21,C22,C23,C24,C25,C26,C27,C28,C29,C30,SAV,SAV1,
9SAV2,SAV3,SAV4,SAV5,SAV6,SAV7,SAV8,SAV9,SC1,THCPR,ENEWST,
XENEWCT,EKP,EKP1,EKP2,EKP3,EKP4,EKP5,ENEWTH,THC1,ENEWM,
XAA,KAC,NRET,SW2,EN(9),PRNOPT,HOLD,J,K,L,STOR(1000)
 ERAS6=EEP5*ERASE
 ERAS7=CNTRL3-DEC1
 ERAS8=ERAS7+DEC2
 ERAS9=SIN(THA)
 ERAS10=COS(THA)
 ERAS11=ERAS9/ERAS10
 ERAS12=ERAS6-DEC1
 ERAS12=EEP5/ERAS12
 ERAS13=DEC2*CNTRL3
 ERAS13=ERAS7/ERAS13
 ERAS14=ERAS2*ERAS2
 ERAS15=ERAS1/ERAS2
 ERAS16=ERAS1*ERAS10
 ERAS16=-ERAS2*ERAS9+ERAS16
 ERAS17=ERAS16*ERAS16
 ERAS18=ERAS2*ERAS10
 ERAS18=ERAS1*ERAS9+ERAS18
 ERAS19=ERAS18*ERAS18
```

```
        ERAS20=ERAS16/ERAS18
        ERAS21=ERAS6-ERAS13
        ERAS21=DEC1/ERAS21
        ERAS22=DEC1/CNTRL3
        ERAS22=(ERAS6*ERAS13+ERAS22)*ERAS6
        ERAS23=-DEC1/ERAS22
        ERAS21=((ERAS23+ERAS21)/ERAS7)*DEC2*CNTRL5*EEP5*ERAS1*ERAS2
        ERAS23=((ERAS8/DEC2)*ERAS12-DEC1)/ERAS14
        ERAS23=-ERAS12*ERAS12*ERAS8*ERASE+ERAS23
        CALLSSR
        CONTINUE
        ERAS22=ERAS11*ERAS11
        ERAS24=-DEC1/ERAS22
        ERAS24=(ERAS24-DEC1)/ERAS23
        ERAS5=ERAS24*ERAS21
        ERAS26=((ERAS8/ERAS7)*ERAS15)/ERAS20
        ERAS26=(ERAS26-DEC1)*ERAS17+DEC1
        ERAS28=ERAS16*ERAS18
        ERAS27=(ERAS28/ERAS14)*ERAS24
        ERAS29=ERAS24-DEC1
        ERAS27=(((ERAS19-ERAS17)*ERAS15*ERAS29+ERAS27)/DEC2)*ERAS8
        ERAS27=-ERAS29*ERAS28*ERAS7+ERAS27
        ERAS35=DEC1/ERAS26
        ERAS3=SQRT(ERAS35)
        ERAS4=((-ERAS35*ERAS3)/ERAS7)*ERAS27
        RETURN
        END
$IBFTC IPT      REF
        SUBROUTINEIPT
        COMMONXA,YA,THA,WA,SMUA,CMUA,STHA,CTHA,SA,XB,YB,THB,
       1WB,SMUB,CMUB,STHB,CTHB,SB,EPB,TEPB,XC,YC,THC,WC,
       2SMUC,CMUC,STHC,CTHC,SC,EPC,TEPC,EMUA,EMUB,EMUC,THAC,
       3WAC,SMUAC,YAC,EMUAC,STHAC,ELAC,THBC,WBC,SMUBC,YBC,EMUBC,
       4STHBC,EPBC,TEPBC,EMBC,TANMA,TANMB,EMC,PC,CPC,EM,THCP,
       5COS1,TAN1,COS2,TAN2,KOUNT,TAPE,ALIGHT,BEGS,SVCON,SVCON1,
       6SVCON2,SVCON3,SVCON4,SVCON5,SVCON6,SVCON7,SVCON8,SVCON9,SVCO10,
       7SVCO11, EEP,EEP1,EEP2,EEP3,EEP4,EEP5,EEP6,EEP7,CNTRL,CNTRL1,
       8CNTRL2,CNTRL3,CNTRL4,CNTRL5,CNTRL6,KNTRL7,CNTRL8,CNTRL9,CNTR10,
       9KNTR11,CNTR12,CNTR13,CNTR14,CNTR15,CNTR16,CNTR17,CNTR18,CNTR19,
       XCNTR54,ERASE,ERAS1,ERAS2,ERAS3,ERAS4,ERAS5,ERAS6,ERAS7,
       XERAS8,ERAS9,ERAS10,ERAS11,ERAS12,ERAS13,ERAS14,ERAS15,ERAS16
        COMMONERAS17,ERAS18,ERAS19,ERAS20,ERAS21,ERAS22,ERAS23,
       1ERAS24,ERAS25,ERAS26,ERAS27,ERAS28,ERAS29,ERAS30,ERAS31,
       2ERAS32,ERAS33,ERAS34,ERAS35,DEC,DEC1,DEC2,DEC3,DEC4,
       3DEC5,DEC6,DEC7,DEC8,DEC9,DEC10,DEC11,KON,CON1,PRT,
```

```
      4PRT1,PRT2,PRT3,PRT4,PRT5,PRT6,PRT7,PRT8,PRT9,DEG,
      5TEMP,TEMP1,TEMP2,TEMP3,TEMP4,XI,YI,THI,WI,SMUI,
      6CMUI,STHI,CTHI,SI,KER10,EX1,EX2,C1,C2,C3,C4,C5,C6,
      7C7,C8,C9,C10,C11,C12,C13,C14,C15,C16,C17,C18,C19,C20,
      8C21,C22,C23,C24,C25,C26,C27,C28,C29,C30,SAV,SAV1,
      9SAV2,SAV3,SAV4,SAV5,SAV6,SAV7,SAV8,SAV9,SC1,THCPR,ENEWST,
      XENEWCT,EKP,EKP1,EKP2,EKP3,EKP4,EKP5,ENEWTH,THC1,ENEWM,
      XAA,KAC,NRET,SW2,EN(9),PRNOPT,HOLD,J,K,L,STOR(1000)
        IF(XC-XA-.01)2,1,1
    2 NRET=6
      RETURN
    1 XI=XA+.01
      TEMP=XC-XA
      TEMP=.01/TEMP
      YI=(YC-YA)*TEMP+YA
      THI=(THC-THA)*TEMP+THA
      WI=(WC-WA)*TEMP+WA
      SI=(SC-SA)*TEMP+SA
      CTHI=COS(THI)
      STHI=SIN(THI)
      TEMP1=WI*WI
      TEMP1=DEC1/TEMP1
      TEMP2=CNTRL3-DEC1
      SMUI=((TEMP1-DEC1)/DEC2)*TEMP2
      CMUI=SQRT(DEC1-SMUI)
      SMUI=SQRT(SMUI)
      NRET=1
      RETURN
      END
$IBFTC SHKPT    REF
      SUBROUTINESHKPT
      COMMONXA,YA,THA,WA,SMUA,CMUA,STHA,CTHA,SA,XB,YB,THB,
     1WB,SMUB,CMUB,STHB,CTHB,SB,EPB,TEPB,XC,YC,THC,WC,
     2SMUC,CMUC,STHC,CTHC,SC,EPC,TEPC,EMUA,EMUB,EMUC,THAC,
     3WAC,SMUAC,YAC,EMUAC,STHAC,ELAC,THBC,WBC,SMUBC,YBC,EMUBC,
     4STHBC,EPBC,TEPBC,EMBC,TANMA,TANMB,EMC,PC,CPC,EM,THCP,
     5COS1,TAN1,COS2,TAN2,KOUNT,TAPE,ALIGHT,BEGS,SVCON,SVCON1,
     6SVCON2,SVCON3,SVCON4,SVCON5,SVCON6,SVCON7,SVCON8,SVCON9,SVCO10,
     7SVCO11, EEP,EEP1,EEP2,EEP3,EEP4,EEP5,EEP6,EEP7,CNTRL,CNTRL1,
     8CNTRL2,CNTRL3,CNTRL4,CNTRL5,CNTRL6,KNTRL7,CNTRL8,CNTRL9,CNTR10,
     9KNTR11,CNTR12,CNTR13,CNTR14,CNTR15,CNTR16,CNTR17,CNTR18,CNTR19,
     XCNTR54,ERASE,ERAS1,ERAS2,ERAS3,ERAS4,ERAS5,ERAS6,ERAS7,
     XERAS8,ERAS9,ERAS10,ERAS11,ERAS12,ERAS13,ERAS14,ERAS15,ERAS16
```

```
      COMMONERAS17,ERAS18,ERAS19,ERAS20,ERAS21,ERAS22,ERAS23,
     1ERAS24,ERAS25,ERAS26,ERAS27,ERAS28,ERAS29,ERAS30,ERAS31,
     2ERAS32,ERAS33,ERAS34,ERAS35,DEC,DEC1,DEC2,DEC3,DEC4,
     3DEC5,DEC6,DEC7,DEC8,DEC9,DEC10,DEC11,KON,CON1,PRT,
     4PRT1,PRT2,PRT3,PRT4,PRT5,PRT6,PRT7,PRT8,PRT9,DEG,
     5TEMP,TEMP1,TEMP2,TEMP3,TEMP4,XI,YI,THI,WI,SMUI,
     6CMUI,STHI,CTHI,SI,KER10,EX1,EX2,C1,C2,C3,C4,C5,C6,
     7C7,C8,C9,C10,C11,C12,C13,C14,C15,C16,C17,C18,C19,C20,
     8C21,C22,C23,C24,C25,C26,C27,C28,C29,C30,SAV,SAV1,
     9SAV2,SAV3,SAV4,SAV5,SAV6,SAV7,SAV8,SAV9,SC1,THCPR,ENEWST,
     XENEWCT,EKP,EKP1,EKP2,EKP3,EKP4,EKP5,ENEWTH,THC1,ENEWM,
     XAA,KAC,NRET,SW2,EN(9),PRNOPT,HOLD,J,K,L,STOR(1000)
       COMMON LTEST,BSHK1
       CONTINUE
       CONTINUE
       THAC=THA
       WAC=WA
       ERASE=SMUA/CMUA
       EMUA=ATAN(ERASE)
       EMUAC=EMUA
       EPBC=EPB
       TEPBC=TEPB
       KOUNT=0
       ERASE=STHA/CTHA
       CALLEPSR
       CALLTHASR
    6  ERAS6=SIN(THAC)
       ERAS7=COS(THAC)
       ERAS8=SIN(EMUAC)
       ERAS9=COS(EMUAC)
       ERAS10=COS(EPBC)
       ERAS10=(SIN(EPBC))/ERAS10
       ERAS11=ERAS8/ERAS9
       ERAS13=ERAS6*ERAS8
       IF(BSHK1)40,40,41
   40  ERAS13=ERAS7*ERAS9-ERAS13
       GO TO 42
   41  ERAS13=ERAS7*ERAS9+ERAS13
   42  ERAS12=ERAS6*ERAS9
       IF(BSHK1)50,50,51
   50  ERAS12=ERAS7*ERAS8+ERAS12
       GO TO 52
   51  ERAS12=-ERAS7*ERAS8+ERAS12
   52  ERAS14=ERAS12/ERAS13
       XC=ERAS14-ERAS10
```

```
       YC=-XB*ERAS10+YB
       XC=(XA*ERAS14-YA+YC)/XC
       YC=XC*ERAS10+YC
       YAC=(YC+YA)/DEC2
       IF(CNTRL8)1,2,1
    2  ELAC=0
       GOTO31
    1  ELAC=(((ERAS8*ERAS8)/ERAS9)*ERAS6)/ERAS13
       ELAC=((XC-XA)/YAC)*ELAC
   31  ERAS15=ERAS4/WAC
       IF(BSHK1)60,60,61
60     ERAS15=ERAS15-ERAS11
       GO TO 62
61     ERAS15=ERAS15+ERAS11
62     ERAS16=(ERAS3-WA)/WAC
       ERAS16=ELAC-ERAS16
       IF(CNTRL9)4,3,4
    4  ERAS18=CNTRL3*CNTRL5
       ERAS18=(ERAS8*ERAS8)/ERAS18
       ERAS15=ERAS18*ERAS5+ERAS15
       ERAS16=(SA-SC)*ERAS18+ERAS16
    3  ERAS15=ERAS16/ERAS15
       THCP=THC
       THC=THA+ERAS15
       CONTINUE
       WC=ERAS4*ERAS15+ERAS3
       CALLMUSR
       IF(DEC)21,20,21
20     EMUAC=(EMUC+EMUA)/DEC2
       WAC=(WA+WC)/DEC2
       THAC=(THA+THC)/DEC2
       ERAS7=COS(THC)
       ERAS6=SIN(THC)
       ERASE=ERAS6/ERAS7
       CALLFPSR
       EPBC=(EPC+EPB)/DEC2
       KOUNT=KOUNT+KON
       IF(KOUNT-KNTRL7)6,5,5
    5  IF(ABS(THC-THCP)-CNTRL6)7,7,6
    7  IF(CNTRL9)9,8,9
    9  CALLSSR
       GOTO10
    8  SC=SA
```

```
        GOTO11
 10     CONTINUE
     11 STHC=SIN(THC)
        CTHC=COS(THC)
        CONTINUE
        CONTINUE
        CONTINUE
        CONTINUE
 21     RETURN
        END
$IBFTC MOVAC    REF
        SUBROUTINEMOVAC
        COMMONXA,YA,THA,WA,SMUA,CMUA,STHA,CTHA,SA,XB,YB,THB,
       1WB,SMUB,CMUB,STHB,CTHB,SB,EPB,TEPB,XC,YC,THC,WC,
       2SMUC,CMUC,STHC,CTHC,SC,EPC,TEPC,EMUA,EMUB,EMUC,THAC,
       3WAC,SMUAC,YAC,EMUAC,STHAC,ELAC,THBC,WBC,SMUBC,YBC,EMUBC,
       4STHBC,EPBC,TEPBC,EMBC,TANMA,TANMB,EMC,PC,CPC,EM,THCP,
       5COS1,TAN1,COS2,TAN2,KOUNT,TAPE,ALIGHT,BEGS,SVCON,SVCON1,
       6SVCON2,SVCON3,SVCON4,SVCON5,SVCON6,SVCON7,SVCON8,SVCON9,SVCO10,
       7SVCO11, EEP,EEP1,EEP2,EEP3,EEP4,EEP5,EEP6,EEP7,CNTRL,CNTRL1,
       8CNTRL2,CNTRL3,CNTRL4,CNTRL5,CNTRL6,KNTRL7,CNTRL8,CNTRL9,CNTR10,
       9KNTR11,CNTR12,CNTR13,CNTR14,CNTR15,CNTR16,CNTR17,CNTR18,CNTR19,
       XCNTR54,ERASE,ERAS1,ERAS2,ERAS3,ERAS4,ERAS5,ERAS6,ERAS7,
       XERAS8,ERAS9,ERAS10,ERAS11,ERAS12,ERAS13,ERAS14,ERAS15,ERAS16
        COMMONERAS17,ERAS18,ERAS19,ERAS20,ERAS21,ERAS22,ERAS23,
       1ERAS24,ERAS25,ERAS26,ERAS27,ERAS28,ERAS29,ERAS30,ERAS31,
       2ERAS32,ERAS33,ERAS34,ERAS35,DEC,DEC1,DEC2,DEC3,DEC4,
       3DEC5,DEC6,DEC7,DEC8,DEC9,DEC10,DEC11,KON,CON1,PRT,
       4PRT1,PRT2,PRT3,PRT4,PRT5,PRT6,PRT7,PRT8,PRT9,DEG,
       5TEMP,TEMP1,TEMP2,TEMP3,TEMP4,XI,YI,THI,WI,SMUI,
       6CMUI,STHI,CTHI,SI,KER10,EX1,EX2,C1,C2,C3,C4,C5,C6,
       7C7,C8,C9,C10,C11,C12,C13,C14,C15,C16,C17,C18,C19,C20,
       8C21,C22,C23,C24,C25,C26,C27,C28,C29,C30,SAV,SAV1,
       9SAV2,SAV3,SAV4,SAV5,SAV6,SAV7,SAV8,SAV9,SC1,THCPR,ENEWST,
       XENEWCT,EKP,EKP1,EKP2,EKP3,EKP4,EKP5,ENEWTH,THC1,ENEWM,
       XAA,KAC,NRET,SW2,EN(9),PRNOPT,HOLD,J,K,L,STOR(1000)
        XC=XA
        YC=YA
        THC=THA
        WC=WA
        SMUC=SMUA
        CMUC=CMUA
        STHC=STHA
        CTHC=CTHA
        SC=SA
```

```
      RETURN
      END
$IBFTC MOVBC    REF
      SUBROUTINEMOVBC
      COMMONXA,YA,THA,WA,SMUA,CMUA,STHA,CTHA,SA,XB,YB,THB,
     1WB,SMUB,CMUB,STHB,CTHB,SB,EPB,TEPB,XC,YC,THC,WC,
     2SMUC,CMUC,STHC,CTHC,SC,EPC,TEPC,EMUA,EMUB,EMUC,THAC,
     3WAC,SMUAC,YAC,EMUAC,STHAC,ELAC,THBC,WBC,SMUBC,YBC,EMUBC,
     4STHBC,EPBC,TEPBC,EMBC,TANMA,TANMB,EMC,PC,CPC,EM,THCP,
     5COS1,TAN1,COS2,TAN2,KOUNT,TAPE,ALIGHT,BEGS,SVCON,SVCON1,
     6SVCON2,SVCON3,SVCON4,SVCON5,SVCON6,SVCON7,SVCON8,SVCON9,SVCO10,
     7SVCO11,EEP,EEP1,EEP2,EEP3,EEP4,EEP5,EEP6,EEP7,CNTRL,CNTRL1,
     8CNTRL2,CNTRL3,CNTRL4,CNTRL5,CNTRL6,KNTRL7,CNTRL8,CNTRL9,CNTR10,
     9KNTR11,CNTR12,CNTR13,CNTR14,CNTR15,CNTR16,CNTR17,CNTR18,CNTR19,
     XCNTR54,ERASE,ERAS1,ERAS2,ERAS3,ERAS4,ERAS5,ERAS6,ERAS7,
     XERAS8,ERAS9,ERAS10,ERAS11,ERAS12,ERAS13,ERAS14,ERAS15,ERAS16
      COMMONERAS17,ERAS18,ERAS19,ERAS20,ERAS21,ERAS22,ERAS23,
     1ERAS24,ERAS25,ERAS26,ERAS27,ERAS28,ERAS29,ERAS30,ERAS31,
     2ERAS32,ERAS33,ERAS34,ERAS35,DEC,DEC1,DEC2,DEC3,DEC4,
     3DEC5,DEC6,DEC7,DEC8,DEC9,DEC10,DEC11,KON,CON1,PRT,
     4PRT1,PRT2,PRT3,PRT4,PRT5,PRT6,PRT7,PRT8,PRT9,DEG,
     5TEMP,TEMP1,TEMP2,TEMP3,TEMP4,XI,YI,THI,WI,SMUI,
     6CMUI,STHI,CTHI,SI,KER10,EX1,EX2,C1,C2,C3,C4,C5,C6,
     7C7,C8,C9,C10,C11,C12,C13,C14,C15,C16,C17,C18,C19,C20,
     8C21,C22,C23,C24,C25,C26,C27,C28,C29,C30,SAV,SAV1,
     9SAV2,SAV3,SAV4,SAV5,SAV6,SAV7,SAV8,SAV9,SC1,THCPR,ENEWST,
     XENEWCT,EKP,EKP1,EKP2,EKP3,EKP4,EKP5,ENEWTH,THC1,ENEWM,
     XAA,KAC,NRET,SW2,EN(9),PRNOPT,HOLD,J,K,L,STOR(1000)
      XC=XB
      YC=YB
      THC=THB
      WC=WB
      SMUC=SMUB
      CMUC=CMUB
      STHC=STHB
      CTHC=CTHB
      SC=SB
      RETURN
      END
$IBFTC BODYX    REF
      SUBROUTINEBODYX
      COMMONXA,YA,THA,WA,SMUA,CMUA,STHA,CTHA,SA,XB,YB,THB,
     1WB,SMUB,CMUB,STHB,CTHB,SB,EPB,TEPB,XC,YC,THC,WC,
```

```
      2SMUC,CMUC,STHC,CTHC,SC,EPC,TEPC,EMUA,EMUB,EMUC,THAC,
      3WAC,SMUAC,YAC,EMUAC,STHAC,ELAC,THBC,WBC,SMUBC,YBC,EMUBC,
      4STHBC,EPBC,TEPBC,EMBC,TANMA,TANMB,EMC,PC,CPC,EM,THCP,
      5COS1,TAN1,COS2,TAN2,KOUNT,TAPE,ALIGHT,BEGS,SVCON,SVCON1,
      6SVCON2,SVCON3,SVCON4,SVCON5,SVCON6,SVCON7,SVCON8,SVCON9,SVCO10,
      7SVCO11, EEP,EEP1,EEP2,EEP3,EEP4,EEP5,EEP6,EEP7,CNTRL,CNTRL1,
      8CNTRL2,CNTRL3,CNTRL4,CNTRL5,CNTRL6,KNTRL7,CNTRL8,CNTRL9,CNTR10,
      9KNTR11,CNTR12,CNTR13,CNTR14,CNTR15,CNTR16,CNTR17,CNTR18,CNTR19,
      XCNTR54,ERASE,ERAS1,ERAS2,ERAS3,ERAS4,ERAS5,ERAS6,ERAS7,
      XERAS8,ERAS9,ERAS10,ERAS11,ERAS12,ERAS13,ERAS14,ERAS15,ERAS16
       COMMONERAS17,ERAS18,ERAS19,ERAS20,ERAS21,ERAS22,ERAS23,
      1ERAS24,ERAS25,ERAS26,ERAS27,ERAS28,ERAS29,ERAS30,ERAS31,
      2ERAS32,ERAS33,ERAS34,ERAS35,DEC,DEC1,DEC2,DEC3,DEC4,
      3DEC5,DEC6,DEC7,DEC8,DEC9,DEC10,DEC11,KON,CON1,PRT,
      4PRT1,PRT2,PRT3,PRT4,PRT5,PRT6,PRT7,PRT8,PRT9,DEG,
      5TEMP,TEMP1,TEMP2,TEMP3,TEMP4,XI,YI,THI,WI,SMUI,
      6CMUI,STHI,CTHI,SI,KER10,EX1,EX2,C1,C2,C3,C4,C5,C6,
      7C7,C8,C9,C10,C11,C12,C13,C14,C15,C16,C17,C18,C19,C20,
      8C21,C22,C23,C24,C25,C26,C27,C28,C29,C30,SAV,SAV1,
      9SAV2,SAV3,SAV4,SAV5,SAV6,SAV7,SAV8,SAV9,SC1,THCPR,ENEWST,
      XENEWCT,EKP,EKP1,EKP2,EKP3,EKP4,EKP5,ENEWTH,THC1,ENEWM,
      XAA,KAC,NRET,SW2,EN(9),PRNOPT,HOLD,J,K,L,STOR(1000)
       THC=ATAN(CNTR16)
       ERASE=SMUB/CMUB
       ERAS1=STHB/CTHB
       ERAS2=-ERAS1*ERASE+DEC1
       ERASE=(ERAS1+ERASE)/ERAS2
       ERAS1=ERASE-CNTR16
       XC=(ERASE*XB-YB+CNTR15)/ERAS1
       YC=XC*CNTR16+CNTR15
       RETURN
       END
$IBFTC RDB2      REF
       SUBROUTINERDB2
       COMMONXA,YA,THA,WA,SMUA,CMUA,STHA,CTHA,SA,XB,YB,THB,
      1WB,SMUB,CMUB,STHB,CTHB,SB,EPB,TEPB,XC,YC,THC,WC,
      2SMUC,CMUC,STHC,CTHC,SC,EPC,TEPC,EMUA,EMUB,EMUC,THAC,
      3WAC,SMUAC,YAC,EMUAC,STHAC,ELAC,THBC,WBC,SMUBC,YBC,EMUBC,
      4STHBC,EPBC,TEPBC,EMBC,TANMA,TANMB,EMC,PC,CPC,EM,THCP,
      5COS1,TAN1,COS2,TAN2,KOUNT,TAPE,ALIGHT,BEGS,SVCON,SVCON1,
      6SVCON2,SVCON3,SVCON4,SVCON5,SVCON6,SVCON7,SVCON8,SVCON9,SVCO10,
      7SVCO11, EEP,EEP1,EEP2,EEP3,EEP4,EEP5,EEP6,EEP7,CNTRL,CNTRL1,
      8CNTRL2,CNTRL3,CNTRL4,CNTRL5,CNTRL6,KNTRL7,CNTRL8,CNTRL9,CNTR10,
      9KNTR11,CNTR12,CNTR13,CNTR14,CNTR15,CNTR16,CNTR17,CNTR18,CNTR19,
      XCNTR54,ERASE,ERAS1,ERAS2,ERAS3,ERAS4,ERAS5,ERAS6,ERAS7,
```

```
      XERAS8,ERAS9,ERAS10,ERAS11,ERAS12,ERAS13,ERAS14,ERAS15,ERAS16
       COMMONERAS17,ERAS18,ERAS19,ERAS20,ERAS21,ERAS22,ERAS23,
      1ERAS24,ERAS25,ERAS26,ERAS27,ERAS28,ERAS29,ERAS30,ERAS31,
      2ERAS32,ERAS33,ERAS34,ERAS35,DEC,DEC1,DEC2,DEC3,DEC4,
      3DEC5,DEC6,DEC7,DEC8,DEC9,DEC10,DEC11,KON,CON1,PRT,
      4PRT1,PRT2,PRT3,PRT4,PRT5,PRT6,PRT7,PRT8,PRT9,DEG,
      5TEMP,TEMP1,TEMP2,TEMP3,TEMP4,XI,YI,THI,WI,SMUI,
      6CMUI,STHI,CTHI,SI,KER10,EX1,EX2,C1,C2,C3,C4,C5,C6,
      7C7,C8,C9,C10,C11,C12,C13,C14,C15,C16,C17,C18,C19,C20,
      8C21,C22,C23,C24,C25,C26,C27,C28,C29,C30,SAV,SAV1,
      9SAV2,SAV3,SAV4,SAV5,SAV6,SAV7,SAV8,SAV9,SC1,THCPR,ENEWST,
      XENEWCT,EKP,EKP1,EKP2,EKP3,EKP4,EKP5,ENEWTH,THC1,ENEWM,
      XAA,KAC,NRET,SW2,EN(9),PRNOPT,HOLD,J,K,L,STOR(1000)
        IF(STOR(J+3))2,1,2
    2 XB=STOR(J)
      YB=STOR(J+1)
      THB=STOR(J+2)
      WB=STOR(J+3)
      SMUB=STOR(J+4)
      CMUB=STOR(J+5)
      STHB=STOR(J+6)
      CTHB=STOR(J+7)
      SB=STOR(J+8)
      J=J+9
      NRET=2
      RETURN
    1 KAC=KNTR11+KON-KER10
      KER10=0
      NRET=1
      RETURN
      END
$IBFTC MOVCA    REF
      SUBROUTINEMOVCA
      COMMONXA,YA,THA,WA,SMUA,CMUA,STHA,CTHA,SA,XB,YB,THB,
      1WB,SMUB,CMUB,STHB,CTHB,SB,EPB,TEPB,XC,YC,THC,WC,
      2SMUC,CMUC,STHC,CTHC,SC,EPC,TEPC,EMUA,EMUB,EMUC,THAC,
      3WAC,SMUAC,YAC,EMUAC,STHAC,ELAC,THBC,WBC,SMUBC,YBC,EMUBC,
      4STHBC,EPBC,TEPBC,EMBC,TANMA,TANMB,EMC,PC,CPC,EM,THCP,
      5COS1,TAN1,COS2,TAN2,KOUNT,TAPE,ALIGHT,BEGS,SVCON,SVCON1,
      6SVCON2,SVCON3,SVCON4,SVCON5,SVCON6,SVCON7,SVCON8,SVCON9,SVCO10,
      7SVCO11, EEP,EEP1,EEP2,EEP3,EEP4,EEP5,EEP6,EEP7,CNTRL,CNTRL1,
      8CNTRL2,CNTRL3,CNTRL4,CNTRL5,CNTRL6,KNTRL7,CNTRL8,CNTRL9,CNTR10,
      9KNTR11,CNTR12,CNTR13,CNTR14,CNTR15,CNTR16,CNTR17,CNTR18,CNTR19,
```

```
      XCNTR54,ERASE,ERAS1,ERAS2,ERAS3,ERAS4,ERAS5,ERAS6,ERAS7,
      XERAS8,ERAS9,ERAS10,ERAS11,ERAS12,ERAS13,ERAS14,ERAS15,ERAS16
       COMMONERAS17,ERAS18,ERAS19,ERAS20,ERAS21,ERAS22,ERAS23,
      1ERAS24,ERAS25,ERAS26,ERAS27,ERAS28,ERAS29,ERAS30,ERAS31,
      2ERAS32,ERAS33,ERAS34,ERAS35,DEC,DEC1,DEC2,DEC3,DEC4,
      3DEC5,DEC6,DEC7,DEC8,DEC9,DEC10,DEC11,KON,CON1,PRT,
      4PRT1,PRT2,PRT3,PRT4,PRT5,PRT6,PRT7,PRT8,PRT9,DEG,
      5TEMP,TEMP1,TEMP2,TEMP3,TEMP4,XI,YI,THI,WI,SMUI,
      6CMUI,STHI,CTHI,SI,KER10,EX1,EX2,C1,C2,C3,C4,C5,C6,
      7C7,C8,C9,C10,C11,C12,C13,C14,C15,C16,C17,C18,C19,C20,
      8C21,C22,C23,C24,C25,C26,C27,C28,C29,C30,SAV,SAV1,
      9SAV2,SAV3,SAV4,SAV5,SAV6,SAV7,SAV8,SAV9,SC1,THCPR,ENEWST,
      XENEWCT,EKP,EKP1,EKP2,EKP3,EKP4,EKP5,ENEWTH,THC1,ENEWM,
      XAA,KAC,NRET,SW2,EN(9),PRNOPT,HOLD,J,K,L,STOR(1000)
       XA=XC
       YA=YC
       THA=THC
       WA=WC
       SMUA=SMUC
       CMUA=CMUC
       STHA=STHC
       CTHA=CTHC
       SA=SC
       RETURN
       END
$IBFTC PRINT    REF
       SUBROUTINEPRINT
       COMMONXA,YA,THA,WA,SMUA,CMUA,STHA,CTHA,SA,XB,YB,THB,
      1WB,SMUB,CMUB,STHB,CTHB,SB,EPB,TEPB,XC,YC,THC,WC,
      2SMUC,CMUC,STHC,CTHC,SC,EPC,TEPC,EMUA,EMUB,EMUC,THAC,
      3WAC,SMUAC,YAC,EMUAC,STHAC,ELAC,THBC,WBC,SMUBC,YBC,EMUBC,
      4STHBC,EPBC,TEPBC,EMBC,TANMA,TANMB,EMC,PC,CPC,EM,THCP,
      5COS1,TAN1,COS2,TAN2,KOUNT,TAPE,ALIGHT,BEGS,SVCON,SVCON1,
      6SVCON2,SVCON3,SVCON4,SVCON5,SVCON6,SVCON7,SVCON8,SVCON9,SVCO10,
      7SVCO11,  EEP,EEP1,EEP2,EEP3,EEP4,EEP5,EEP6,EEP7,CNTRL,CNTRL1,
      8CNTRL2,CNTRL3,CNTRL4,CNTRL5,CNTRL6,KNTRL7,CNTRL8,CNTRL9,CNTR10,
      9KNTR11,CNTR12,CNTR13,CNTR14,CNTR15,CNTR16,CNTR17,CNTR18,CNTR19,
      XCNTR54,ERASE,ERAS1,ERAS2,ERAS3,ERAS4,ERAS5,ERAS6,ERAS7,
      XERAS8,ERAS9,ERAS10,ERAS11,ERAS12,ERAS13,ERAS14,ERAS15,ERAS16
       COMMONERAS17,ERAS18,ERAS19,ERAS20,ERAS21,ERAS22,ERAS23,
      1ERAS24,ERAS25,ERAS26,ERAS27,ERAS28,ERAS29,ERAS30,ERAS31,
      2ERAS32,ERAS33,ERAS34,ERAS35,DEC,DEC1,DEC2,DEC3,DEC4,
      3DEC5,DEC6,DEC7,DEC8,DEC9,DEC10,DEC11,KON,CON1,PRT,
      4PRT1,PRT2,PRT3,PRT4,PRT5,PRT6,PRT7,PRT8,PRT9,DEG,
      5TEMP,TEMP1,TEMP2,TEMP3,TEMP4,XI,YI,THI,WI,SMUI,
```

```
      6CMUI,STHI,CTHI,SI,KER10,EX1,EX2,C1,C2,C3,C4,C5,C6,
      7C7,C8,C9,C10,C11,C12,C13,C14,C15,C16,C17,C18,C19,C20,
      8C21,C22,C23,C24,C25,C26,C27,C28,C29,C30,SAV,SAV1,
      9SAV2,SAV3,SAV4,SAV5,SAV6,SAV7,SAV8,SAV9,SC1,THCPR,ENEWST,
      XENEWCT,EKP,EKP1,EKP2,EKP3,EKP4,EKP5,ENEWTH,THC1,ENEWM,
      XAA,KAC,NRET,SW2,EN(9),PRNOPT,HOLD,J,K,L,STOR(1000)
       ERASE=CNTRL3-DEC1
       ERAS2=ERASE/DEC2
       ERAS3=ERAS2*EEP5+DEC1
       ERAS4=-CNTRL3/ERASE
       ERAS5=(CNTRL3*EEP5)/DEC2
       EMC=DEC1/SMUC
       ERASE=(EMC*EMC*ERAS2+DEC1)/ERAS3
       ERASE=EXP(ALOG(ERASE)*ERAS4)
       ERAS1=-SC/CNTRL5
       PC=EXP(ERAS1)*ERASE
       CPC=(PC-DEC1)/ERAS5
       THD=THC*DEG
       WRITE(6,100)XC,YC,THD,EMC,WC,SC,PC,CPC
  100  FORMAT(8E16.8)
       RETURN
       END
$IBFTC MUSR     REF
       SUBROUTINEMUSR
       COMMONXA,YA,THA,WA,SMUA,CMUA,STHA,CTHA,SA,XB,YB,THB,
      1WB,SMUB,CMUB,STHB,CTHB,SB,EPB,TEPB,XC,YC,THC,WC,
      2SMUC,CMUC,STHC,CTHC,SC,EPC,TEPC,EMUA,EMUB,EMUC,THAC,
      3WAC,SMUAC,YAC,EMUAC,STHAC,ELAC,THBC,WBC,SMUBC,YBC,EMUBC,
      4STHBC,EPBC,TEPBC,EMBC,TANMA,TANMB,EMC,PC,CPC,EM,THCP,
      5COS1,TAN1,COS2,TAN2,KOUNT,TAPE,ALIGHT,BEGS,SVCON,SVCON1,
      6SVCON2,SVCON3,SVCON4,SVCON5,SVCON6,SVCON7,SVCON8,SVCON9,SVCO10,
      7SVCO11, EEP,EEP1,EEP2,EEP3,EEP4,EEP5,EEP6,EEP7,CNTRL,CNTRL1,
      8CNTRL2,CNTRL3,CNTRL4,CNTRL5,CNTRL6,KNTRL7,CNTRL8,CNTRL9,CNTR10,
      9KNTR11,CNTR12,CNTR13,CNTR14,CNTR15,CNTR16,CNTR17,CNTR18,CNTR19,
      XCNTR54,ERASE,ERAS1,ERAS2,ERAS3,ERAS4,ERAS5,ERAS6,ERAS7,
      XERAS8,ERAS9,ERAS10,ERAS11,ERAS12,ERAS13,ERAS14,ERAS15,ERAS16
       COMMONERAS17,ERAS18,ERAS19,ERAS20,ERAS21,ERAS22,ERAS23,
      1ERAS24,ERAS25,ERAS26,ERAS27,ERAS28,ERAS29,ERAS30,ERAS31,
      2ERAS32,ERAS33,ERAS34,ERAS35,DEC,DEC1,DEC2,DEC3,DEC4,
      3DEC5,DEC6,DEC7,DEC8,DEC9,DEC10,DEC11,KON,CON1,PRT,
      4PRT1,PRT2,PRT3,PRT4,PRT5,PRT6,PRT7,PRT8,PRT9,DEG,
      5TEMP,TEMP1,TEMP2,TEMP3,TEMP4,XI,YI,THI,WI,SMUI,
      6CMUI,STHI,CTHI,SI,KER10,EX1,EX2,C1,C2,C3,C4,C5,C6,
```

```
      7C7,C8,C9,C10,C11,C12,C13,C14,C15,C16,C17,C18,C19,C20,
      8C21,C22,C23,C24,C25,C26,C27,C28,C29,C30,SAV,SAV1,
      9SAV2,SAV3,SAV4,SAV5,SAV6,SAV7,SAV8,SAV9,SC1,THCPR,ENEWST,
      XENEWCT,EKP,EKP1,EKP2,EKP3,EKP4,EKP5,ENEWTH,THC1,ENEWM,
      XAA,KAC,NRET,SW2,EN(9),PRNOPT,HOLD,J,K,L,STOR(1000)
        ERASE=WC*WC
        ERASE=DEC1/ERASE
        ERAS1=CNTRL3-DEC1
        SMUC=((ERASE-DEC1)/DEC2)*ERAS1
        IF(DEC1-SMUC)2,1,1
    2   CMUC=(DEC1-SMUC)
        GO TO 3
    1 CMUC=SQRT(DEC1-SMUC)
    3   IF(SMUC)4,5,5
    4   SMUC=SMUC
        GO TO 6
    5 SMUC=SQRT(SMUC)
    6   ERASE=SMUC/CMUC
        EMUC=ATAN(ERASE)
        RETURN
        END
$IBFTC MAIN     REF
C       MAINPROGRAM-SECONDSHOCKREGION
        COMMONXA,YA,THA,WA,SMUA,CMUA,STHA,CTHA,SA,XB,YB,THB,
      1WB,SMUB,CMUB,STHB,CTHB,SB,EPB,TEPB,XC,YC,THC,WC,
      2SMUC,CMUC,STHC,CTHC,SC,EPC,TEPC,EMUA,EMUB,EMUC,THAC,
      3WAC,SMUAC,YAC,EMUAC,STHAC,ELAC,THBC,WBC,SMUBC,YBC,EMUBC,
      4STHBC,EPBC,TEPBC,EMBC,TANMA,TANMB,EMC,PC,CPC,EM,THCP,
      5COS1,TAN1,COS2,TAN2,KOUNT,TAPE,ALIGHT,BEGS,SVCON,SVCON1,
      6SVCON2,SVCON3,SVCON4,SVCON5,SVCON6,SVCON7,SVCON8,SVCON9,SVCO10,
      7SVCO11, EEP,EEP1,EEP2,EEP3,EEP4,EEP5,EEP6,EEP7,CNTRL,CNTRL1,
      8CNTRL2,CNTRL3,CNTRL4,CNTRL5,CNTRL6,KNTRL7,CNTRL8,CNTRL9,CNTR10,
      9KNTR11,CNTR12,CNTR13,CNTR14,CNTR15,CNTR16,CNTR17,CNTR18,CNTR19,
      XCNTR54,ERASE,ERAS1,ERAS2,ERAS3,ERAS4,ERAS5,ERAS6,ERAS7,
      XERAS8,ERAS9,ERAS10,ERAS11,ERAS12,ERAS13,ERAS14,ERAS15,ERAS16
        COMMONERAS17,ERAS18,ERAS19,ERAS20,ERAS21,ERAS22,ERAS23,
      1ERAS24,ERAS25,ERAS26,ERAS27,ERAS28,ERAS29,ERAS30,ERAS31,
      2ERAS32,ERAS33,ERAS34,ERAS35,DEC,DEC1,DEC2,DEC3,DEC4,
      3DEC5,DEC6,DEC7,DEC8,DEC9,DEC10,DEC11,KON,CON1,PRT,
      4PRT1,PRT2,PRT3,PRT4,PRT5,PRT6,PRT7,PRT8,PRT9,DEG,
      5TEMP,TEMP1,TEMP2,TEMP3,TEMP4,XI,YI,THI,WI,SMUI,
      6CMUI,STHI,CTHI,SI,KER10,EX1,EX2,C1,C2,C3,C4,C5,C6,
      7C7,C8,C9,C10,C11,C12,C13,C14,C15,C16,C17,C18,C19,C20,
      8C21,C22,C23,C24,C25,C26,C27,C28,C29,C30,SAV,SAV1,
      9SAV2,SAV3,SAV4,SAV5,SAV6,SAV7,SAV8,SAV9,SC1,THCPR,ENEWST,
```

```
      XENEWCT,EKP,EKP1,EKP2,EKP3,EKP4,EKP5,ENEWTH,THC1,ENEWM,
      XAA,KAC,NRET,SW2,EN(9),PRNOPT,HOLD,J,K,L,STOR(1000)
       TAPE=2.
       ALIGHT=0
       DEC=0
       DEC1=1.
       DEC2=2.
       DEC3=1.570796327
       DEC4=6.283185308
       DEC5=0
       DEC6=0
       DEC7=7
       DEC8=0
       DEC9=9
       DEC10=0
       DEC11=11
       KON=1
       CON1=3.
       DEG=57.2957795
    9 CALLSLITE(0)
      WRITE(6,98)
98    FORMAT(1H1,1HX,13X,1HY,13X,9HTHETA DEG,5X,1HM,13X,1HW,13X,1HS,13X,
      16HPT/PT11X20H(PT/PT1)M(1-W**2)**31X25H((PT/PT1)**2)M(1-W**2)**3)
      DO 999 NN=1,1000
999   STOR(NN)=0
      HOLD=1.
      J=1
      K=1
      L=1
      CALLSLITE(2)
      KER10=0
      CALL FINP(16,CNTRL,CNTRL1,CNTRL3,CNTRL5,CNTR15,CNTR16,EM1,XB,YB,
      1XA,YA,EMB,THB,SB,EPB,PRNOPT)
      EPB=EPB/DEG
      THB=THB/DEG
      CNTRL6=9999.
      KNTRL7=3
      CNTRL8=1.
      CNTRL9=1.
      KNTR11=0
      SW2=0
      WB=SQRT(DEC1/(DEC1+DEC2/((CNTRL3-DEC1)*EMB*EMB)))
      SMUB=DEC1/EMB
```

```
          SMUA=SMUB
          CMUB=SQRT(1.-SMUB*SMUB)
          CMUA=CMUB
          STHB=SIN(THB)
          CTHB=COS(THB)
          STHA=STHB
          CTHA=CTHB
          SA=SB
          WA=WB
          THA=THB
          TEPB=SIN(EPB)/COS(EPB)
          BEGS=EPB
          CALLSHKPT
          IF(DEC)3610,30,3610
   30     CALL PRINT
          CALLWRTSK
          CALLMOVCB
          CALLBODY
          IF(DEC)3610,31,3610
   31     CALL MOVCS
          CALLMOVBA
          CALLIPT
          GOTO(22,22,22,23),NRET
   22     CALLMOVIC
          CALLWRTGN
          CALLPRINT
   23     CALLMOVSC
          CALLWRTGN
          CALLPRINT
          CALLSPACE
          CALLWRTFL
    7     CALLRDB
          GOTO(10,11),NRET
   10     CALLEXIT
   11     CALLRDA
          GOTO(12,13),NRET
   12     CALLEXIT
   13     CALLSHKPT
          IF(DEC)3610,32,3610
   32     CALL PRINT
          CALLWRTSK
          CALLMOVCB
          CALLRDA
          GOTO(14,15),NRET
   14     CALLEXIT
```

```
   15 CALLGEN
      IF(DEC)3610,33,3610
33    GO TO 16
   17 CALLMOVBA
      CALLIPT
      GOTO(24,24,24,25),NRET
   24 CALLMOVIC
      CALLWRTGN
      CALLPRINT
   25 CALLMOVSC
      CALLWRTGN
      CALLPRINT
    4 CALLRDA
      GOTO(18,19),NRET
   18 GOTO1
   19 CALLMOVCB
      CALLGEN
      IF(DEC)3610,34,3610
34    CALL WRTGN
      IF(PRNOPT)3,2,3
    3 CALLPRINT
    2 GOTO4
    1 CALLMOVCB
      L=1
      IF(EN(L+1))20,21,20
   21 XA=EN(L)
      YA=EN(L+1)
      THA=EN(L+2)
      WA=EN(L+3)
      SMUA=EN(L+4)
      CMUA=EN(L+5)
      STHA=EN(L+6)
      CTHA=EN(L+7)
      SA=EN(L+8)
      GOTO20
   20 CALLBODY
      IF(DEC)3610,35,3610
35    CALL WRTGN
      CALLPRINT
3610  DEC=0
      CALL SPACE
      CALLWRTFL
      IF(XC-CNTRL1)6,6,5
```

```
      6  IF(SW2)8,7,8
      8  WRITE(6,100)TAPE,ALIGHT
      5  GOTO9    .
     16  CALLMOVCS
         L=1
         EN(L)=XA
         EN(L+1)=YA
         EN(L+2)=THA
         EN(L+3)=WA
         EN(L+4)=SMUA
         EN(L+5)=CMUA
         EN(L+6)=STHA
         EN(L+7)=CTHA
         EN(L+8)=SA
         GOTO17
    100  FORMAT(2E16.8)
         END
$IBFTC NEWB      REF
       SUBROUTINENEWB
       COMMONXA,YA,THA,WA,SMUA,CMUA,STHA,CTHA,SA,XB,YB,THB,
      1WB,SMUB,CMUB,STHB,CTHB,SB,EPB,TEPB,XC,YC,THC,WC,
      2SMUC,CMUC,STHC,CTHC,SC,EPC,TEPC,EMUA,EMUB,EMUC,THAC,
      3WAC,SMUAC,YAC,EMUAC,STHAC,ELAC,THBC,WBC,SMUBC,YBC,EMUBC,
      4STHBC,EPBC,TEPBC,EMBC,TANMA,TANMB,EMC,PC,CPC,EM,THCP,
      5COS1,TAN1,COS2,TAN2,KOUNT,TAPE,ALIGHT,BEGS,SVCON,SVCON1,
      6SVCON2,SVCON3,SVCON4,SVCON5,SVCON6,SVCON7,SVCON8,SVCON9,SVCO10,
      7SVCO11, EEP,EEP1,EEP2,EEP3,EEP4,EEP5,EEP6,EEP7,CNTRL,CNTRL1,
      8CNTRL2,CNTRL3,CNTRL4,CNTRL5,CNTRL6,KNTRL7,CNTRL8,CNTRL9,CNTR10,
      9KNTR11,CNTR12,CNTR13,CNTR14,CNTR15,CNTR16,CNTR17,CNTR18,CNTR19,
      XCNTR54,ERASE,ERAS1,ERAS2,ERAS3,ERAS4,ERAS5,ERAS6,ERAS7,
      XERAS8,ERAS9,ERAS10,ERAS11,ERAS12,ERAS13,ERAS14,ERAS15,ERAS16
       COMMONERAS17,ERAS18,ERAS19,ERAS20,ERAS21,ERAS22,ERAS23,
      1ERAS24,ERAS25,ERAS26,ERAS27,ERAS28,ERAS29,ERAS30,ERAS31,
      2ERAS32,ERAS33,ERAS34,ERAS35,DEC,DEC1,DEC2,DEC3,DEC4,
      3DEC5,DEC6,DEC7,DEC8,DEC9,DEC10,DEC11,KON,CON1,PRT,
      4PRT1,PRT2,PRT3,PRT4,PRT5,PRT6,PRT7,PRT8,PRT9,DEG,
      5TEMP,TEMP1,TEMP2,TEMP3,TEMP4,XI,YI,THI,WI,SMUI,
      6CMUI,STHI,CTHI,SI,KER10,EX1,EX2,C1,C2,C3,C4,C5,C6,
      7C7,C8,C9,C10,C11,C12,C13,C14,C15,C16,C17,C18,C19,C20,
      8C21,C22,C23,C24,C25,C26,C27,C28,C29,C30,SAV,SAV1,
      9SAV2,SAV3,SAV4,SAV5,SAV6,SAV7,SAV8,SAV9,SC1,THCPR,ENEWST,
      XENEWCT,EKP,EKP1,EKP2,EKP3,EKP4,EKP5,ENEWTH,THC1,ENEWM,
      XAA,KAC,NRET,SW2,EN(9),PRNOPT,HOLD,J,K,L,STOR(1000)
       SAV=CMUA/SMUA
       IF(STHA)5,4,5
```

```
    4 SAV4=SMUA/CMUA
      GOTO3
    5 SAV1=CTHA/STHA
      SAV3=DEC1/SAV1
      IF(SAV)2,1,2
    2 SAV2=DEC1/SAV
      SAV4=-SAV2*SAV3+DEC1
      SAV4=(SAV3+SAV2)/SAV4
      GOTO3
    1 SAV4=-SAV1
    3 SAV5=XB*TEPB-YB+YA
      SAV5=-XA*SAV4+SAV5
      SAV6=TEPB-SAV4
      XC=SAV5/SAV6
      SAV5=XC-XB
      YC=SAV5*TEPB+YB
      CALLSUBR
      ENEWTH=THC1+THA
      ENEWCT=COS(ENEWTH)
      ENEWST=SIN(ENEWTH)
      EKP5=ENEWM*ENEWM
      EKP1=EKP5+EKP5
      EKP4=EKP1+DEC1
      EKP=EKP5*EKP5
      EKP3=((CNTRL3+DEC1)/DEC2)*EKP5+DEC1
      EKP1=-EKP3*EKP1
      EKP2=-(EKP5+DEC2)*EKP5
      RETURN
      END
$IBFTC PRINT    REF
      SUBROUTINEPRINT
      COMMONXA,YA,THA,WA,SMUA,CMUA,STHA,CTHA,SA,XB,YB,THB,
     1WB,SMUB,CMUB,STHB,CTHB,SB,EPB,TEPB,XC,YC,THC,WC,
     2SMUC,CMUC,STHC,CTHC,SC,EPC,TEPC,EMUA,EMUB,EMUC,THAC,
     3WAC,SMUAC,YAC,EMUAC,STHAC,ELAC,THBC,WBC,SMUBC,YBC,EMUBC,
     4STHBC,EPBC,TEPBC,EMBC,TANMA,TANMB,EMC,PC,CPC,EM,THCP,
     5COS1,TAN1,COS2,TAN2,KOUNT,TAPE,ALIGHT,BEGS,SVCON,SVCON1,
     6SVCON2,SVCON3,SVCON4,SVCON5,SVCON6,SVCON7,SVCON8,SVCON9,SVCO10,
     7SVCO11,  EEP,EEP1,EEP2,EEP3,EEP4,EEP5,EEP6,EEP7,CNTRL,CNTRL1,
     8CNTRL2,CNTRL3,CNTRL4,CNTRL5,CNTRL6,KNTRL7,CNTRL8,CNTRL9,CNTR10,
     9KNTR11,CNTR12,CNTR13,CNTR14,CNTR15,CNTR16,CNTR17,CNTR18,CNTR19,
     XCNTR54,ERASE,ERAS1,ERAS2,ERAS3,ERAS4,ERAS5,ERAS6,ERAS7,
     XERAS8,ERAS9,ERAS10,ERAS11,ERAS12,ERAS13,ERAS14,ERAS15,ERAS16
```

```
      COMMONERAS17,ERAS18,ERAS19,ERAS20,ERAS21,ERAS22,ERAS23,
     1ERAS24,ERAS25,ERAS26,ERAS27,ERAS28,ERAS29,ERAS30,ERAS31,
     2ERAS32,ERAS33,ERAS34,ERAS35,DEC,DEC1,DEC2,DEC3,DEC4,
     3DEC5,DEC6,DEC7,DEC8,DEC9,DEC10,DEC11,KON,CON1,PRT,
     4PRT1,PRT2,PRT3,PRT4,PRT5,PRT6,PRT7,PRT8,PRT9,DEG,
     5TEMP,TEMP1,TEMP2,TEMP3,TEMP4,XI,YI,THI,WI,SMUI,
     6CMUI,STHI,CTHI,SI,KER10,EX1,EX2,C1,C2,C3,C4,C5,C6,
     7C7,C8,C9,C10,C11,C12,C13,C14,C15,C16,C17,C18,C19,C20,
     8C21,C22,C23,C24,C25,C26,C27,C28,C29,C30,SAV,SAV1,
     9SAV2,SAV3,SAV4,SAV5,SAV6,SAV7,SAV8,SAV9,SC1,THCPR,ENEWST,
     XENEWCT,EKP,EKP1,EKP2,EKP3,EKP4,EKP5,ENEWTH,THC1,ENEWM,
     XAA,KAC,NRET,SW2,EN(9),PRNOPT,HOLD,J,K,L,STOR(1000)
      EMC=DEC1/SMUC
      TEMP=-SC/CNTRL5
      TEMP=EXP(TEMP)
      TEMP1=-WC*WC+DEC1
      TEMP1=TEMP1*TEMP1*TEMP1*EMC*TEMP
      TEMP2=TEMP1*TEMP
      THD=THC*DEG
      WRITE(6,100)XC,YC,THD,EMC,WC,SC,TEMP,TEMP1,TEMP2
      RETURN
  100 FORMAT(9E14.6)
      END
$IBFTC EPSR      REF
      SUBROUTINEEPSR
      COMMONXA,YA,THA,WA,SMUA,CMUA,STHA,CTHA,SA,XB,YB,THB,
     1WB,SMUB,CMUB,STHB,CTHB,SB,EPB,TEPB,XC,YC,THC,WC,
     2SMUC,CMUC,STHC,CTHC,SC,EPC,TEPC,EMUA,EMUB,EMUC,THAC,
     3WAC,SMUAC,YAC,EMUAC,STHAC,ELAC,THBC,WBC,SMUBC,YBC,EMUBC,
     4STHBC,EPBC,TEPBC,EMBC,TANMA,TANMB,EMC,PC,CPC,EM,THCP,
     5COS1,TAN1,COS2,TAN2,KOUNT,TAPE,ALIGHT,BEGS,SVCON,SVCON1,
     6SVCON2,SVCON3,SVCON4,SVCON5,SVCON6,SVCON7,SVCON8,SVCON9,SVCO10,
     7SVCO11,  EEP,EEP1,EEP2,EEP3,EEP4,EEP5,EEP6,EEP7,CNTRL,CNTRL1,
     8CNTRL2,CNTRL3,CNTRL4,CNTRL5,CNTRL6,KNTRL7,CNTRL8,CNTRL9,CNTR10,
     9KNTR11,CNTR12,CNTR13,CNTR14,CNTR15,CNTR16,CNTR17,CNTR18,CNTR19,
     XCNTR54,ERASE,ERAS1,ERAS2,ERAS3,ERAS4,ERAS5,ERAS6,ERAS7,
     XERAS8,ERAS9,ERAS10,ERAS11,ERAS12,ERAS13,ERAS14,ERAS15,ERAS16
      COMMONERAS17,ERAS18,ERAS19,ERAS20,ERAS21,ERAS22,ERAS23,
     1ERAS24,ERAS25,ERAS26,ERAS27,ERAS28,ERAS29,ERAS30,ERAS31,
     2ERAS32,ERAS33,ERAS34,ERAS35,DEC,DEC1,DEC2,DEC3,DEC4,
     3DEC5,DEC6,DEC7,DEC8,DEC9,DEC10,DEC11,KON,CON1,PRT,
     4PRT1,PRT2,PRT3,PRT4,PRT5,PRT6,PRT7,PRT8,PRT9,DEG,
     5TEMP,TEMP1,TEMP2,TEMP3,TEMP4,XI,YI,THI,WI,SMUI,
     6CMUI,STHI,CTHI,SI,KER10,EX1,EX2,C1,C2,C3,C4,C5,C6,
     7C7,C8,C9,C10,C11,C12,C13,C14,C15,C16,C17,C18,C19,C20,
```

```
      8C21,C22,C23,C24,C25,C26,C27,C28,C29,C30,SAV,SAV1,
      9SAV2,SAV3,SAV4,SAV5,SAV6,SAV7,SAV8,SAV9,SC1,THCPR,ENEWST,
      XENEWCT,EKP,EKP1,EKP2,EKP3,EKP4,EKP5,ENEWTH,THC1,ENEWM,
      XAA,KAC,NRET,SW2,EN(9),PRNOPT,HOLD,J,K,L,STOR(1000)
        ERASE=ERASE*ERASE
        ERAS1=ERASE*EKP+EKP
        ERAS2=(ERASE*EKP1+EKP2)/CON1
        ERAS13=(EKP3*EKP3*ERASE+EKP4)/CON1
        ERAS6=ERAS13*ERAS2+ERAS1
        ERAS9=ERAS2*ERAS2
        ERAS15=ERAS1*ERAS13-ERAS9
        ERASE=ERAS15+ERAS15
        ERAS10=(ERAS6/ERASE)*ERAS1+ERAS2
        ERAS6=ERAS6*ERAS6
        ERAS7=ERAS13*ERAS13+ERAS2
        AA=(SQRT(ABS((ERAS7+ERAS7)*ERASE+ERAS6))/ERASE)*ERAS1
        AA=ATAN2(AA,ERAS10)
        IF(AA)2,2,1
      2 AA=AA+DEC4
      1 ERASE=AA/CON1
        ERASE=COS(ERASE)
        ERAS9=SQRT(-ERAS15)
        ERASE=-((ERAS9+ERAS9)*ERASE+ERAS2)/ERAS1
        ERAS2=SQRT(DEC1-ERASE)
        ERAS1=SQRT(ERASE)
        TEPC=ERAS1/ERAS2
        EPC=ATAN(TEPC)
        RETURN
        END
$IBFTC BODY      REF
        SUBROUTINEBODY
        COMMONXA,YA,THA,WA,SMUA,CMUA,STHA,CTHA,SA,XB,YB,THB,
      1WB,SMUB,CMUB,STHB,CTHB,SB,EPB,TEPB,XC,YC,THC,WC,
      2SMUC,CMUC,STHC,CTHC,SC,EPC,TEPC,EMUA,EMUB,EMUC,THAC,
      3WAC,SMUAC,YAC,EMUAC,STHAC,ELAC,THBC,WBC,SMUBC,YBC,EMUBC,
      4STHBC,EPBC,TEPBC,EMBC,TANMA,TANMB,EMC,PC,CPC,EM,THCP,
      5COS1,TAN1,COS2,TAN2,KOUNT,TAPE,ALIGHT,BEGS,SVCON,SVCON1,
      6SVCON2,SVCON3,SVCON4,SVCON5,SVCON6,SVCON7,SVCON8,SVCON9,SVCO10,
      7SVCO11,  EEP,EEP1,EEP2,EEP3,EEP4,EEP5,EEP6,EEP7,CNTRL,CNTRL1,
      8CNTRL2,CNTRL3,CNTRL4,CNTRL5,CNTRL6,KNTRL7,CNTRL8,CNTRL9,CNTR10,
      9KNTR11,CNTR12,CNTR13,CNTR14,CNTR15,CNTR16,CNTR17,CNTR18,CNTR19,
      XCNTR54,ERASE,ERAS1,ERAS2,ERAS3,ERAS4,ERAS5,ERAS6,ERAS7,
      XERAS8,ERAS9,ERAS10,ERAS11,ERAS12,ERAS13,ERAS14,ERAS15,ERAS16
```

```
      COMMONERAS17,ERAS18,ERAS19,ERAS20,ERAS21,ERAS22,ERAS23,
     1ERAS24,ERAS25,ERAS26,ERAS27,ERAS28,ERAS29,ERAS30,ERAS31,
     2ERAS32,ERAS33,ERAS34,ERAS35,DEC,DEC1,DEC2,DEC3,DEC4,
     3DEC5,DEC6,DEC7,DEC8,DEC9,DEC10,DEC11,KON,CON1,PRT,
     4PRT1,PRT2,PRT3,PRT4,PRT5,PRT6,PRT7,PRT8,PRT9,DEG,
     5TEMP,TEMP1,TEMP2,TEMP3,TEMP4,XI,YI,THI,WI,SMUI,
    -6CMUI,STHI,CTHI,SI,KER10,EX1,EX2,C1,C2,C3,C4,C5,C6,
     7C7,C8,C9,C10,C11,C12,C13,C14,C15,C16,C17,C18,C19,C20,
     8C21,C22,C23,C24,C25,C26,C27,C28,C29,C30,SAV,SAV1,
     9SAV2,SAV3,SAV4,SAV5,SAV6,SAV7,SAV8,SAV9,SC1,THCPR,ENEWST,
     XENEWCT,EKP,EKP1,EKP2,EKP3,EKP4,EKP5,ENEWTH,THC1,ENEWM,
     XAA,KAC,NRET,SW2,EN(9),PRNOPT,HOLD,J,K,L,STOR(1000)
      COMMON LTEST
      WBC=WB
      KOUNT=0
      ERAS2=SMUB/CMUB
      EMUB=ATAN(ERAS2)
      SC=SA
    9 THCP=THC
      CALLBODYX
      IF(CNTRL8)2,1,2
    2 ERASE=CTHB*CMUB
      ERAS1=STHB*SMUB
      ERASE=ERAS1+ERASE
      ERAS2=SMUB/CMUB
      ERASE=(ERAS2*ERAS1)/ERASE
      YBC=(YB+YC)/DEC2
      ERASE=((XC-XB)/YBC)*ERASE
      GOTO3
    1 ERASE=0
    3 CALLSLITET(2,LTEST)
      GOTO(5,4),LTEST
    5 CALLSLITE(2)
      GOTO6
    4 AA=0
      GOTO7
    6 IF(CNTRL9)8,7,8
    8 AA=((((SC-SB)/CNTRL3)*SMUB)/CNTRL5)*SMUB
    7 ERASE=AA-ERASE
      WC=((THB-THC)*ERAS2-ERASE)*WBC+WB
      CALLMUSR
      IF(DEC)21,20,21
   20 EMUB=(EMUC+EMUB)/DEC2
      SMUB=SIN(EMUB)
      CMUB=COS(EMUB)
```

```
      THBC=(THB+THC)/DEC2
      STHB=SIN(THBC)
      CTHB=COS(THBC)
      WBC=(WB+WC)/DEC2
      KOUNT=(KOUNT+KON)
      IF(KOUNT-KNTRL7)9,10,10
   10 IF(ABS(THC-THCP)-CNTRL6)11,11,9
   11 STHC=SIN(THC)
      CTHC=COS(THC)
   21 RETURN
      END
$IBFTC THASR   REF
      SUBROUTINETHASR
      COMMONXA,YA,THA,WA,SMUA,CMUA,STHA,CTHA,SA,XB,YB,THB,
     1WB,SMUB,CMUB,STHB,CTHB,SB,EPB,TEPB,XC,YC,THC,WC,
     2SMUC,CMUC,STHC,CTHC,SC,EPC,TEPC,EMUA,EMUB,EMUC,THAC,
     3WAC,SMUAC,YAC,EMUAC,STHAC,ELAC,THBC,WBC,SMUBC,YBC,EMUBC,
     4STHBC,EPBC,TEPBC,EMBC,TANMA,TANMB,EMC,PC,CPC,EM,THCP,
     5COS1,TAN1,COS2,TAN2,KOUNT,TAPE,ALIGHT,BEGS,SVCON,SVCON1,
     6SVCON2,SVCON3,SVCON4,SVCON5,SVCON6,SVCON7,SVCON8,SVCON9,SVCO10,
     7SVCO11, EEP,EEP1,EEP2,EEP3,EEP4,EEP5,EEP6,EEP7,CNTRL,CNTRL1,
     8CNTRL2,CNTRL3,CNTRL4,CNTRL5,CNTRL6,KNTRL7,CNTRL8,CNTRL9,CNTR10,
     9KNTR11,CNTR12,CNTR13,CNTR14,CNTR15,CNTR16,CNTR17,CNTR18,CNTR19,
     XCNTR54,ERASE,ERAS1,ERAS2,ERAS3,ERAS4,ERAS5,ERAS6,ERAS7,
     XERAS8,ERAS9,ERAS10,ERAS11,ERAS12,ERAS13,ERAS14,ERAS15,ERAS16
      COMMONERAS17,ERAS18,ERAS19,ERAS20,ERAS21,ERAS22,ERAS23,
     1ERAS24,ERAS25,ERAS26,ERAS27,ERAS28,ERAS29,ERAS30,ERAS31,
     2ERAS32,ERAS33,ERAS34,ERAS35,DEC,DEC1,DEC2,DEC3,DEC4,
     3DEC5,DEC6,DEC7,DEC8,DEC9,DEC10,DEC11,KON,CON1,PRT,
     4PRT1,PRT2,PRT3,PRT4,PRT5,PRT6,PRT7,PRT8,PRT9,DEG,
     5TEMP,TEMP1,TEMP2,TEMP3,TEMP4,XI,YI,THI,WI,SMUI,
     6CMUI,STHI,CTHI,SI,KER10,EX1,EX2,C1,C2,C3,C4,C5,C6,
     7C7,C8,C9,C10,C11,C12,C13,C14,C15,C16,C17,C18,C19,C20,
     8C21,C22,C23,C24,C25,C26,C27,C28,C29,C30,SAV,SAV1,
     9SAV2,SAV3,SAV4,SAV5,SAV6,SAV7,SAV8,SAV9,SC1,THCPR,ENEWST,
     XENEWCT,EKP,EKP1,EKP2,EKP3,EKP4,EKP5,ENEWTH,THC1,ENEWM,
     XAA,KAC,NRET,SW2,EN(9),PRNOPT,HOLD,J,K,L,STOR(1000)
      ERAS6=EKP5*ERASE
      ERAS7=CNTRL3-DEC1
      ERAS8=ERAS7+DEC2
      ERAS9=SIN(ENEWTH)
      ERAS10=COS(ENEWTH)
      ERAS11=ERAS9/ERAS10
```

```
      ERAS12=ERAS6-DEC1
      ERAS12=EKP5/ERAS12
      ERAS13=DEC2*CNTRL3
      ERAS13=ERAS7/ERAS13
      ERAS14=ERAS2*ERAS2
      ERAS15=ERAS1/ERAS2
      ERAS16=ERAS1*ERAS10
      ERAS16=-ERAS2*ERAS9+ERAS16
      ERAS17=ERAS16*ERAS16
      ERAS18=ERAS2*ERAS10
      ERAS18=ERAS1*ERAS9+ERAS18
      ERAS19=ERAS18*ERAS18
      ERAS20=ERAS16/ERAS18
      ERAS21=ERAS6-ERAS13
      ERAS21=DEC1/ERAS21
      ERAS22=DEC1/CNTRL3
      ERAS22=(ERAS6*ERAS13+ERAS22)*ERAS6
      ERAS23=-DEC1/ERAS22
      ERAS21=((ERAS23+ERAS21)/ERAS7)*DEC2*CNTRL5*EKP5*ERAS1*ERAS2
      ERAS23=((ERAS8/DEC2)*ERAS12-DEC1)/ERAS14
      ERAS23=-ERAS12*ERAS12*ERAS8*ERASE+ERAS23
      CALLSSR
      SC=SC+SC1
      ERAS22=ERAS11*ERAS11
      ERAS24=-DEC1/ERAS22
      ERAS24=(ERAS24-DEC1)/ERAS23
      ERAS5=ERAS24*ERAS21
      ERAS26=((ERAS8/ERAS7)*ERAS15)/ERAS20
      ERAS26=(ERAS26-DEC1)*ERAS17+DEC1
      ERAS28=ERAS16*ERAS18
      ERAS27=(ERAS28/ERAS14)*ERAS24
      ERAS29=ERAS24-DEC1
      ERAS27=(((ERAS19-ERAS17)*ERAS15*ERAS29+ERAS27)/DEC2)*ERAS8
      ERAS27=-ERAS29*ERAS28*ERAS7+ERAS27
      ERAS35=DEC1/ERAS26
      ERAS3=SQRT(ERAS35)
      ERAS4=((-ERAS35*ERAS3)/ERAS7)*ERAS27
      RETURN
      END
$IBFTC MUSR      REF
      SUBROUTINEMUSR
      COMMONXA,YA,THA,WA,SMUA,CMUA,STHA,CTHA,SA,XB,YB,THB,
     1WB,SMUB,CMUB,STHB,CTHB,SB,EPB,TEPB,XC,YC,THC,WC,
     2SMUC,CMUC,STHC,CTHC,SC,EPC,TEPC,EMUA,EMUB,EMUC,THAC,
     3WAC,SMUAC,YAC,EMUAC,STHAC,ELAC,THBC,WBC,SMUBC,YBC,EMUBC,
```

```
      4STHBC,EPBC,TEPBC,EMBC,TANMA,TANMB,EMC,PC,CPC,EM,THCP,
      5COS1,TAN1,COS2,TAN2,KOUNT,TAPE,ALIGHT,BEGS,SVCON,SVCON1,
      6SVCON2,SVCON3,SVCON4,SVCON5,SVCON6,SVCON7,SVCON8,SVCON9,SVCO10,
      7SVCO11, EEP,EEP1,EEP2,EEP3,EEP4,EEP5,EEP6,EEP7,CNTRL,CNTRL1,
      8CNTRL2,CNTRL3,CNTRL4,CNTRL5,CNTRL6,KNTRL7,CNTRL8,CNTRL9,CNTR10,
      9KNTR11,CNTR12,CNTR13,CNTR14,CNTR15,CNTR16,CNTR17,CNTR18,CNTR19,
      XCNTR54,ERASE,ERAS1,ERAS2,ERAS3,ERAS4,ERAS5,ERAS6,ERAS7,
      XERAS8,ERAS9,ERAS10,ERAS11,ERAS12,ERAS13,ERAS14,ERAS15,ERAS16
        COMMONERAS17,ERAS18,ERAS19,ERAS20,ERAS21,ERAS22,ERAS23,
      1ERAS24,ERAS25,ERAS26,ERAS27,ERAS28,ERAS29,ERAS30,ERAS31,
      2ERAS32,ERAS33,ERAS34,ERAS35,DEC,DEC1,DEC2,DEC3,DEC4,
      3DEC5,DEC6,DEC7,DEC8,DEC9,DEC10,DEC11,KON,CON1,PRT,
      4PRT1,PRT2,PRT3,PRT4,PRT5,PRT6,PRT7,PRT8,PRT9,DEG,
      5TEMP,TEMP1,TEMP2,TEMP3,TEMP4,XI,YI,THI,WI,SMUI,
      6CMUI,STHI,CTHI,SI,KER10,EX1,EX2,C1,C2,C3,C4,C5,C6,
      7C7,C8,C9,C10,C11,C12,C13,C14,C15,C16,C17,C18,C19,C20,
      8C21,C22,C23,C24,C25,C26,C27,C28,C29,C30,SAV,SAV1,
      9SAV2,SAV3,SAV4,SAV5,SAV6,SAV7,SAV8,SAV9,SC1,THCPR,ENEWST,
      XENEWCT,EKP,EKP1,EKP2,EKP3,EKP4,EKP5,ENEWTH,THC1,ENEWM,
      XAA,KAC,NRET,SW2,EN(9),PRNOPT,HOLD,J,K,L,STOR(1000)
        ERASE=WC*WC
        ERASE=DEC1/ERASE
        ERAS1=CNTRL3-DEC1
        SMUC=((ERASE-DEC1)/DEC2)*ERAS1
        IF(DEC1-SMUC)3610,1,1
    1   CMUC=SQRT(DEC1-SMUC)
        SMUC=SQRT(SMUC)
        ERASE=SMUC/CMUC
        EMUC=ATAN(ERASE)
        RETURN
 3610   DEC=1.
        RETURN
        END
$IBFTC IPT      REF
        SUBROUTINEIPT
        COMMONXA,YA,THA,WA,SMUA,CMUA,STHA,CTHA,SA,XB,YB,THB,
      1WB,SMUB,CMUB,STHB,CTHB,SB,EPB,TEPB,XC,YC,THC,WC,
      2SMUC,CMUC,STHC,CTHC,SC,EPC,TEPC,EMUA,EMUB,EMUC,THAC,
      3WAC,SMUAC,YAC,EMUAC,STHAC,ELAC,THBC,WBC,SMUBC,YBC,EMUBC,
      4STHBC,EPBC,TEPBC,EMBC,TANMA,TANMB,EMC,PC,CPC,EM,THCP,
      5COS1,TAN1,COS2,TAN2,KOUNT,TAPE,ALIGHT,BEGS,SVCON,SVCON1,
      6SVCON2,SVCON3,SVCON4,SVCON5,SVCON6,SVCON7,SVCON8,SVCON9,SVCO10,
      7SVCO11, EEP,EEP1,EEP2,EEP3,EEP4,EEP5,EEP6,EEP7,CNTRL,CNTRL1,
```

```
      8CNTRL2,CNTRL3,CNTRL4,CNTRL5,CNTRL6,KNTRL7,CNTRL8,CNTRL9,CNTR10,
      9KNTR11,CNTR12,CNTR13,CNTR14,CNTR15,CNTR16,CNTR17,CNTR18,CNTR19,
      XCNTR54,ERASE,ERAS1,ERAS2,ERAS3,ERAS4,ERAS5,ERAS6,ERAS7,
      XERAS8,ERAS9,ERAS10,ERAS11,ERAS12,ERAS13,ERAS14,ERAS15,ERAS16
       COMMONERAS17,ERAS18,ERAS19,ERAS20,ERAS21,ERAS22,ERAS23,
      1ERAS24,ERAS25,ERAS26,ERAS27,ERAS28,ERAS29,ERAS30,ERAS31,
      2ERAS32,ERAS33,ERAS34,ERAS35,DEC,DEC1,DEC2,DEC3,DEC4,
      3DEC5,DEC6,DEC7,DEC8,DEC9,DEC10,DEC11,KON,CONT,PRT,
      4PRT1,PRT2,PRT3,PRT4,PRT5,PRT6,PRT7,PRT8,PRT9,DEG,
      5TEMP,TEMP1,TEMP2,TEMP3,TEMP4,XI,YI,THI,WI,SMUI,
      6CMUI,STHI,CTHI,SI,KER10,EX1,EX2,C1,C2,C3,C4,C5,C6,
      7C7,C8,C9,C10,C11,C12,C13,C14,C15,C16,C17,C18,C19,C20,
      8C21,C22,C23,C24,C25,C26,C27,C28,C29,C30,SAV,SAV1,
      9SAV2,SAV3,SAV4,SAV5,SAV6,SAV7,SAV8,SAV9,SC1,THCPR,ENEWST,
      XENEWCT,EKP,EKP1,EKP2,EKP3,EKP4,EKP5,ENEWTH,THC1,ENEWM,
      XAA,KAC,NRET,SW2,EN(9),PRNOPT,HOLD,J,K,L,STOR(1000)
       IF(XC-XA-.01)2,1,1
    2 NRET=4
      RETURN
    1 XI=XA+.01
      TEMP=XC-XA
      TEMP=.01/TEMP
      YI=(YC-YA)*TEMP+YA
      THI=(THC-THA)*TEMP+THA
      WI=(WC-WA)*TEMP+WA
      SI=(SC-SA)*TEMP+SA
      CTHI=COS(THI)
      STHI=SIN(THI)
      TEMP1=WI*WI
      TEMP1=DEC1/TEMP1
      TEMP2=CNTRL3-DEC1
      SMUI=((TEMP1-DEC1)/DEC2)*TEMP2
      CMUI=SQRT(DEC1-SMUI)
      SMUI=SQRT(SMUI)
      NRET=1
      RETURN
      END
$IBFTC SHKPT    REF
      SUBROUTINESHKPT
      COMMONXA,YA,THA,WA,SMUA,CMUA,STHA,CTHA,SA,XB,YB,THB,
      1WB,SMUB,CMUB,STHB,CTHB,SB,EPB,TEPB,XC,YC,THC,WC,
      2SMUC,CMUC,STHC,CTHC,SC,EPC,TEPC,EMUA,EMUB,EMUC,THAC,
      3WAC,SMUAC,YAC,EMUAC,STHAC,ELAC,THBC,WBC,SMUBC,YBC,EMUBC,
      4STHBC,EPBC,TEPBC,EMBC,TANMA,TANMB,EMC,PC,CPC,EM,THCP,
      5COS1,TAN1,COS2,TAN2,KOUNT,TAPE,ALIGHT,BEGS,SVCON,SVCON1,
```

```
6SVCON2,SVCON3,SVCON4,SVCON5,SVCON6,SVCON7,SVCON8,SVCON9,SVCO10,
7SVCO11, EEP,EEP1,EEP2,EEP3,EEP4,EEP5,EEP6,EEP7,CNTRL,CNTRL1,
8CNTRL2,CNTRL3,CNTRL4,CNTRL5,CNTRL6,KNTRL7,CNTRL8,CNTRL9,CNTR10,
9KNTR11,CNTR12,CNTR13,CNTR14,CNTR15,CNTR16,CNTR17,CNTR18,CNTR19,
XCNTR54,ERASE,ERAS1,ERAS2,ERAS3,ERAS4,ERAS5,ERAS6,ERAS7,
XERAS8,ERAS9,ERAS10,ERAS11,ERAS12,ERAS13,ERAS14,ERAS15,ERAS16
  COMMONERAS17,ERAS18,ERAS19,ERAS20,ERAS21,ERAS22,ERAS23,
1ERAS24,ERAS25,ERAS26,ERAS27,ERAS28,ERAS29,ERAS30,ERAS31,
2ERAS32,ERAS33,ERAS34,ERAS35,DEC,DEC1,DEC2,DEC3,DEC4,
3DEC5,DEC6,DEC7,DEC8,DEC9,DEC10,DEC11,KON,CON1,PRT,
4PRT1,PRT2,PRT3,PRT4,PRT5,PRT6,PRT7,PRT8,PRT9,DEG,
5TEMP,TEMP1,TEMP2,TEMP3,TEMP4,XI,YI,THI,WI,SMUI,
6CMUI,STHI,CTHI,SI,KER10,EX1,EX2,C1,C2,C3,C4,C5,C6,
7C7,C8,C9,C10,C11,C12,C13,C14,C15,C16,C17,C18,C19,C20,
8C21,C22,C23,C24,C25,C26,C27,C28,C29,C30,SAV,SAV1,
9SAV2,SAV3,SAV4,SAV5,SAV6,SAV7,SAV8,SAV9,SC1,THCPR,ENEWST,
XENEWCT,EKP,EKP1,EKP2,EKP3,EKP4,EKP5,ENEWTH,THC1,ENEWM,
XAA,KAC,NRET,SW2,FN(9),PRNOPT,HOLD,J,K,L,STOR(1000)
  CALLNEWB
  HOLD=-1.
  THAC=THA
  WAC=WA
  ERASE=SMUA/CMUA
  EMUA=ATAN(ERASE)
  EMUAC=EMUA
  EPBC=EPB
  TEPBC=TEPB
  KOUNT=0
  ERASE=ENEWST/ENEWCT
  CALLEPSR
  CALLTHASR
6 ERAS6=SIN(THAC)
  ERAS7=COS(THAC)
  ERAS8=SIN(EMUAC)
  ERAS9=COS(EMUAC)
  ERAS10=COS(EPBC)
  ERAS10=(SIN(EPBC))/ERAS10
  ERAS11=ERAS8/ERAS9
  ERAS13=ERAS6*ERAS8
  ERAS13=ERAS7*ERAS9-ERAS13
  ERAS12=ERAS6*ERAS9
  ERAS12=ERAS7*ERAS8+ERAS12
  ERAS14=ERAS12/ERAS13
```

```
       XC=ERAS14-ERAS10
       YC=-XB*ERAS10+YB
       XC=(XA*ERAS14-YA+YC)/XC
       YC=XC*ERAS10+YC
       YAC=(YC+YA)/DEC2
       IF(CNTRL8)1,2,1
     2 ELAC=0
       GOTO31
     1 ELAC=(((ERAS8*ERAS8)/ERAS9)*ERAS6)/ERAS13
       ELAC=((XC-XA)/YAC)*ELAC
    31 ERAS15=ERAS4/WAC
       ERAS15=ERAS15-ERAS11
       ERAS16=(ERAS3-WA)/WAC
       ERAS16=ELAC-ERAS16
       IF(CNTRL9)4,3,4
     4 ERAS18=CNTRL3*CNTRL5
       ERAS18=(ERAS8*ERAS8)/ERAS18
       ERAS15=ERAS18*ERAS5+ERAS15
       ERAS16=(SA-SC)*ERAS18+ERAS16
     3 ERAS15=ERAS16/ERAS15
       THCP=THC
       THC=THA+ERAS15
       THCPR=THC+THC1
       WC=ERAS4*ERAS15+ERAS3
       CALLMUSR
       IF(DEC)21,20,21
    20 EMUAC=(EMUC+EMUA)/DEC2
       WAC=(WA+WC)/DEC2
       THAC=(THA+THC)/DEC2
       ERAS7=COS(THCPR)
       ERAS6=SIN(THCPR)
       ERASE=ERAS6/ERAS7
       CALLEPSR
       EPBC=(EPC+EPB-THC1)/DEC2
       KOUNT=KOUNT+KON
       IF(KOUNT-KNTRL7)6,5,5
     5 IF(ABS(THC-THCP)-CNTRL6)7,7,6
     7 IF(CNTRL9)9,8,9
     9 CALLSSR
       GOTO10
     8 SC=SA
       GOTO11
    10 SC=SC+SC1
    11 STHC=SIN(THC)
       CTHC=COS(THC)
```

```
      EPC=EPC-THC1
      SAV=COS(EPC)
      TEPC=SIN(EPC)/SAV
      HOLD=1.
   21 RETURN
      END
$IBFTC BODYX    REF
      SUBROUTINEBODYX
      COMMONXA,YA,THA,WA,SMUA,CMUA,STHA,CTHA,SA,XB,YB,THB,
     1WB,SMUB,CMUB,STHB,CTHB,SB,EPB,TEPB,XC,YC,THC,WC,
     2SMUC,CMUC,STHC,CTHC,SC,EPC,TEPC,EMUA,EMUB,EMUC,THAC,
     3WAC,SMUAC,YAC,EMUAC,STHAC,ELAC,THBC,WBC,SMUBC,YBC,EMUBC,
     4STHBC,EPBC,TEPBC,EMBC,TANMA,TANMB,EMC,PC,CPC,EM,THCP,
     5COS1,TAN1,COS2,TAN2,KOUNT,TAPE,ALIGHT,BEGS,SVCON,SVCON1,
     6SVCON2,SVCON3,SVCON4,SVCON5,SVCON6,SVCON7,SVCON8,SVCON9,SVCO10,
     7SVCO11, EEP,EEP1,EEP2,EEP3,EEP4,EEP5,EEP6,EEP7,CNTRL,CNTRL1,
     8CNTRL2,CNTRL3,CNTRL4,CNTRL5,CNTRL6,KNTRL7,CNTRL8,CNTRL9,CNTR10,
     9KNTR11,CNTR12,CNTR13,CNTR14,CNTR15,CNTR16,CNTR17,CNTR18,CNTR19,
     XCNTR54,ERASE,ERAS1,ERAS2,ERAS3,ERAS4,ERAS5,ERAS6,ERAS7,
     XERAS8,ERAS9,ERAS10,ERAS11,ERAS12,ERAS13,ERAS14,ERAS15,ERAS16
      COMMONERAS17,ERAS18,ERAS19,ERAS20,ERAS21,ERAS22,ERAS23,
     1ERAS24,ERAS25,ERAS26,ERAS27,ERAS28,ERAS29,ERAS30,ERAS31,
     2ERAS32,ERAS33,ERAS34,ERAS35,DEC,DEC1,DEC2,DEC3,DEC4,
     3DEC5,DEC6,DEC7,DEC8,DEC9,DEC10,DEC11,KON,CON1,PRT,
     4PRT1,PRT2,PRT3,PRT4,PRT5,PRT6,PRT7,PRT8,PRT9,DEG,
     5TEMP,TEMP1,TEMP2,TEMP3,TEMP4,XI,YI,THI,WI,SMUI,
     6CMUI,STHI,CTHI,SI,KER10,EX1,EX2,C1,C2,C3,C4,C5,C6,
     7C7,C8,C9,C10,C11,C12,C13,C14,C15,C16,C17,C18,C19,C20,
     8C21,C22,C23,C24,C25,C26,C27,C28,C29,C30,SAV,SAV1,
     9SAV2,SAV3,SAV4,SAV5,SAV6,SAV7,SAV8,SAV9,SC1,THCPR,ENEWST,
     XENEWCT,EKP,EKP1,EKP2,EKP3,EKP4,EKP5,ENEWTH,THC1,ENEWM,
     XAA,KAC,NRET,SW2,EN(9),PRNOPT,HOLD,J,K,L,STOR(1000)
      YC=0
      THC=0
      ERASE=SMUB/CMUB
      ERAS1=STHB/CTHB
      ERAS2=ERAS1*ERASE+DEC1
      ERASE=(ERAS1-ERASE)/ERAS2
      XC=(ERASE*XB-YB)/ERASE
      RETURN
C     CENTERLINEBODY
      END
$IBFTC SUBR     REF
```

```
      SUBROUTINESUBR
      COMMONXA,YA,THA,WA,SMUA,CMUA,STHA,CTHA,SA,XB,YB,THB,
     1WB,SMUB,CMUB,STHB,CTHB,SB,EPB,TEPB,XC,YC,THC,WC,
     2SMUC,CMUC,STHC,CTHC,SC,EPC,TEPC,EMUA,EMUB,EMUC,THAC,
     3WAC,SMUAC,YAC,EMUAC,STHAC,ELAC,THBC,WBC,SMUBC,YBC,EMUBC,
     4STHBC,EPBC,TEPBC,EMBC,TANMA,TANMB,EMC,PC,CPC,EM,THCP,
     5COS1,TAN1,COS2,TAN2,KOUNT,TAPE,ALIGHT,BEGS,SVCON,SVCON1,
     6SVCON2,SVCON3,SVCON4,SVCON5,SVCON6,SVCON7,SVCON8,SVCON9,SVCO10,
     7SVCO11, EEP,EEP1,EEP2,EEP3,EEP4,EEP5,EEP6,EEP7,CNTRL,CNTRL1,
     8CNTRL2,CNTRL3,CNTRL4,CNTRL5,CNTRL6,KNTRL7,CNTRL8,CNTRL9,CNTR10,
     9KNTR11,CNTR12,CNTR13,CNTR14,CNTR15,CNTR16,CNTR17,CNTR18,CNTR19,
     XCNTR54,ERASE,ERAS1,ERAS2,ERAS3,ERAS4,ERAS5,ERAS6,ERAS7,
     XERAS8,ERAS9,ERAS10,ERAS11,ERAS12,ERAS13,ERAS14,ERAS15,ERAS16
      COMMONERAS17,ERAS18,ERAS19,ERAS20,ERAS21,ERAS22,ERAS23,
     1ERAS24,ERAS25,ERAS26,ERAS27,ERAS28,ERAS29,ERAS30,ERAS31,
     2ERAS32,ERAS33,ERAS34,ERAS35,DEC,DEC1,DEC2,DEC3,DEC4,
     3DEC5,DEC6,DEC7,DEC8,DEC9,DEC10,DEC11,KON,CON1,PRT,
     4PRT1,PRT2,PRT3,PRT4,PRT5,PRT6,PRT7,PRT8,PRT9,DEG,
     5TEMP,TEMP1,TEMP2,TEMP3,TEMP4,XI,YI,THI,WI,SMUI,
     6CMUI,STHI,CTHI,SI,KER10,EX1,EX2,C1,C2,C3,C4,C5,C6,
     7C7,C8,C9,C10,C11,C12,C13,C14,C15,C16,C17,C18,C19,C20,
     8C21,C22,C23,C24,C25,C26,C27,C28,C29,C30,SAV,SAV1,
     9SAV2,SAV3,SAV4,SAV5,SAV6,SAV7,SAV8,SAV9,SC1,THCPR,ENEWST,
     XENEWCT,EKP,EKP1,EKP2,EKP3,EKP4,EKP5,ENEWTH,THC1,ENEWM,
     XAA,KAC,NRET,SW2,EN(9),PRNOPT,HOLD,J,K,L,STOR(1000)
      ENEWM=2.685947+.725327*YC+SQRT(-17.506468*YC*YC
     1+7.870908*YC-.152477)-(1.6-2.857*YC)*(XC-(YC+.7479)/.277)
      THC1=-.0325/(YC**.6475)-1.65*YC**2.795+.0424*(XC-
     1(YC+.7479)/.277)/YC**1.068
      THC1=-THC1
      SC1=153./YC**.675
      RETURN
      END
$IBFTC MOVIC    REF
      SUBROUTINEMOVIC
C
C     THESE SUBROUTINES USED IN BOTH FIRST AND SECOND SHOCK REGIONS
C
      COMMONXA,YA,THA,WA,SMUA,CMUA,STHA,CTHA,SA,XB,YB,THB,
     1WB,SMUB,CMUB,STHB,CTHB,SB,EPB,TEPB,XC,YC,THC,WC,
     2SMUC,CMUC,STHC,CTHC,SC,EPC,TEPC,EMUA,EMUB,EMUC,THAC,
     3WAC,SMUAC,YAC,EMUAC,STHAC,ELAC,THBC,WBC,SMUBC,YBC,EMUBC,
     4STHBC,EPBC,TEPBC,EMBC,TANMA,TANMB,EMC,PC,CPC,EM,THCP,
     5COS1,TAN1,COS2,TAN2,KOUNT,TAPE,ALIGHT,BEGS,SVCON,SVCON1,
     6SVCON2,SVCON3,SVCON4,SVCON5,SVCON6,SVCON7,SVCON8,SVCON9,SVCO10,
```

```
      7SVCO11, EEP,EEP1,EEP2,EEP3,EEP4,EEP5,EEP6,EEP7,CNTRL,CNTRL1,
      8CNTRL2,CNTRL3,CNTRL4,CNTRL5,CNTRL6,KNTRL7,CNTRL8,CNTRL9,CNTR10,
      9KNTR11,CNTR12,CNTR13,CNTR14,CNTR15,CNTR16,CNTR17,CNTR18,CNTR19,
      XCNTR54,ERASE,ERAS1,ERAS2,ERAS3,ERAS4,ERAS5,ERAS6,ERAS7,
      XERAS8,ERAS9,ERAS10,ERAS11,ERAS12,ERAS13,ERAS14,ERAS15,ERAS16
       COMMONERAS17,ERAS18,ERAS19,ERAS20,ERAS21,ERAS22,ERAS23,
      1ERAS24,ERAS25,ERAS26,ERAS27,ERAS28,ERAS29,ERAS30,ERAS31,
      2ERAS32,ERAS33,ERAS34,ERAS35,DEC,DEC1,DEC2,DEC3,DEC4,
      3DEC5,DEC6,DEC7,DEC8,DEC9,DEC10,DEC11,KON,CON1,PRT,
      4PRT1,PRT2,PRT3,PRT4,PRT5,PRT6,PRT7,PRT8,PRT9,DEG,
      5TEMP,TEMP1,TEMP2,TEMP3,TEMP4,XI,YI,THI,WI,SMUI,
      6CMUI,STHI,CTHI,SI,KER10,EX1,EX2,C1,C2,C3,C4,C5,C6,
      7C7,C8,C9,C10,C11,C12,C13,C14,C15,C16,C17,C18,C19,C20,
      8C21,C22,C23,C24,C25,C26,C27,C28,C29,C30,SAV,SAV1,
      9SAV2,SAV3,SAV4,SAV5,SAV6,SAV7,SAV8,SAV9,SC1,THCPR,ENEWST,
      XENEWCT,EKP,EKP1,EKP2,EKP3,EKP4,EKP5,ENEWTH,THC1,ENEWM,
      XAA,KAC,NRET,SW2,EN(9),PRNOPT,HOLD,J,K,L,STOR(1000)
       XC=XI
       YC=YI
       THC=THI
       WC=WI
       SMUC=SMUI
       CMUC=CMUI
       STHC=STHI
       CTHC=CTHI
       SC=SI
       RETURN
       END
$IBFTC MOVCS    REF
       SUBROUTINEMOVCS
       COMMONXA,YA,THA,WA,SMUA,CMUA,STHA,CTHA,SA,XB,YB,THB,
      1WB,SMUB,CMUB,STHB,CTHB,SB,EPB,TEPB,XC,YC,THC,WC,
      2SMUC,CMUC,STHC,CTHC,SC,EPC,TEPC,EMUA,EMUB,EMUC,THAC,
      3WAC,SMUAC,YAC,EMUAC,STHAC,ELAC,THBC,WBC,SMUBC,YBC,EMUBC,
      4STHBC,EPBC,TEPBC,EMBC,TANMA,TANMB,EMC,PC,CPC,EM,THCP,
      5COS1,TAN1,COS2,TAN2,KOUNT,TAPE,ALIGHT,BEGS,SVCON,SVCON1,
      6SVCON2,SVCON3,SVCON4,SVCON5,SVCON6,SVCON7,SVCON8,SVCON9,SVCO10,
      7SVCO11, EEP,EEP1,EEP2,EEP3,EEP4,EEP5,EEP6,EEP7,CNTRL,CNTRL1,
      8CNTRL2,CNTRL3,CNTRL4,CNTRL5,CNTRL6,KNTRL7,CNTRL8,CNTRL9,CNTR10,
      9KNTR11,CNTR12,CNTR13,CNTR14,CNTR15,CNTR16,CNTR17,CNTR18,CNTR19,
      XCNTR54,ERASE,ERAS1,ERAS2,ERAS3,ERAS4,ERAS5,ERAS6,ERAS7,
      XERAS8,ERAS9,ERAS10,ERAS11,ERAS12,ERAS13,ERAS14,ERAS15,ERAS16
       COMMONERAS17,ERAS18,ERAS19,ERAS20,ERAS21,ERAS22,ERAS23,
```

```
     1ERAS24,ERAS25,ERAS26,ERAS27,ERAS28,ERAS29,ERAS30,ERAS31,
     2ERAS32,ERAS33,ERAS34,ERAS35,DEC,DEC1,DEC2,DEC3,DEC4,
     3DEC5,DEC6,DEC7,DEC8,DEC9,DEC10,DEC11,KON,CON1,PRT,
     4PRT1,PRT2,PRT3,PRT4,PRT5,PRT6,PRT7,PRT8,PRT9,DEG,
     5TEMP,TEMP1,TEMP2,TEMP3,TEMP4,XI,YI,THI,WI,SMUI,
     6CMUI,STHI,CTHI,SI,KER10,EX1,EX2,C1,C2,C3,C4,C5,C6,
     7C7,C8,C9,C10,C11,C12,C13,C14,C15,C16,C17,C18,C19,C20,
     8C21,C22,C23,C24,C25,C26,C27,C28,C29,C30,SAV,SAV1,
     9SAV2,SAV3,SAV4,SAV5,SAV6,SAV7,SAV8,SAV9,SC1,THCPR,ENEWST,
     XENEWCT,EKP,EKP1,EKP2,EKP3,EKP4,EKP5,ENEWTH,THC1,ENEWM,
     XAA,KAC,NRET,SW2,EN(9),PRNOPT,HOLD,J,K,L,STOR(1000)
       SAV=XC
       SAV1=YC
       SAV2=THC
       SAV3=WC
       SAV4=SMUC
       SAV5=CMUC
       SAV6=STHC
       SAV7=CTHC
       SAV8=SC
       RETURN
       END
$IBFTC MOVSC    REF
       SUBROUTINEMOVSC
       COMMONXA,YA,THA,WA,SMUA,CMUA,STHA,CTHA,SA,XB,YB,THB,
     1WB,SMUB,CMUB,STHB,CTHB,SB,EPB,TEPB,XC,YC,THC,WC,
     2SMUC,CMUC,STHC,CTHC,SC,EPC,TEPC,EMUA,EMUB,EMUC,THAC,
     3WAC,SMUAC,YAC,EMUAC,STHAC,ELAC,THBC,WBC,SMUBC,YBC,EMUBC,
     4STHBC,EPBC,TEPBC,EMBC,TANMA,TANMB,EMC,PC,CPC,EM,THCP,
     5COS1,TAN1,COS2,TAN2,KOUNT,TAPE,ALIGHT,BEGS,SVCON,SVCON1,
     6SVCON2,SVCON3,SVCON4,SVCON5,SVCON6,SVCON7,SVCON8,SVCON9,SVCO10,
     7SVCO11,  EEP,EEP1,EEP2,EEP3,EEP4,EEP5,EEP6,EEP7,CNTRL,CNTRL1,
     8CNTRL2,CNTRL3,CNTRL4,CNTRL5,CNTRL6,KNTRL7,CNTRL8,CNTRL9,CNTR10,
     9KNTR11,CNTR12,CNTR13,CNTR14,CNTR15,CNTR16,CNTR17,CNTR18,CNTR19,
     XCNTR54,ERASE,ERAS1,ERAS2,ERAS3,ERAS4,ERAS5,ERAS6,ERAS7,
     XERAS8,ERAS9,ERAS10,ERAS11,ERAS12,ERAS13,ERAS14,ERAS15,ERAS16
       COMMONERAS17,ERAS18,ERAS19,ERAS20,ERAS21,ERAS22,ERAS23,
     1ERAS24,ERAS25,ERAS26,ERAS27,ERAS28,ERAS29,ERAS30,ERAS31,
     2ERAS32,ERAS33,ERAS34,ERAS35,DEC,DEC1,DEC2,DEC3,DEC4,
     3DEC5,DEC6,DEC7,DEC8,DEC9,DEC10,DEC11,KON,CON1,PRT,
     4PRT1,PRT2,PRT3,PRT4,PRT5,PRT6,PRT7,PRT8,PRT9,DEG,
     5TEMP,TEMP1,TEMP2,TEMP3,TEMP4,XI,YI,THI,WI,SMUI,
     6CMUI,STHI,CTHI,SI,KER10,EX1,EX2,C1,C2,C3,C4,C5,C6,
     7C7,C8,C9,C10,C11,C12,C13,C14,C15,C16,C17,C18,C19,C20,
     8C21,C22,C23,C24,C25,C26,C27,C28,C29,C30,SAV,SAV1,
```

```
      9SAV2,SAV3,SAV4,SAV5,SAV6,SAV7,SAV8,SAV9,SC1,THCPR,ENEWST,
      XENEWCT,EKP,EKP1,EKP2,EKP3,EKP4,EKP5,ENEWTH,THC1,ENEWM,
      XAA,KAC,NRET,SW2,EN(9),PRNOPT,HOLD,J,K,L,STOR(1000)
        XC=SAV
        YC=SAV1
        THC=SAV2
        WC=SAV3
        SMUC=SAV4
        CMUC=SAV5
        STHC=SAV6
        CTHC=SAV7
        SC=SAV8
        RETURN
        END
$IBFTC MOVBA    REF
        SUBROUTINEMOVBA
        COMMONXA,YA,THA,WA,SMUA,CMUA,STHA,CTHA,SA,XB,YB,THB,
      1WB,SMUB,CMUB,STHB,CTHB,SB,EPB,TEPB,XC,YC,THC,WC,
      2SMUC,CMUC,STHC,CTHC,SC,EPC,TEPC,EMUA,EMUB,EMUC,THAC,
      3WAC,SMUAC,YAC,EMUAC,STHAC,ELAC,THBC,WBC,SMUBC,YBC,EMUBC,
      4STHBC,EPBC,TEPBC,EMBC,TANMA,TANMB,EMC,PC,CPC,EM,THCP,
      5COS1,TAN1,COS2,TAN2,KOUNT,TAPE,ALIGHT,BEGS,SVCON,SVCON1,
      6SVCON2,SVCON3,SVCON4,SVCON5,SVCON6,SVCON7,SVCON8,SVCON9,SVCO10,
      7SVCO11,EEP,EEP1,EEP2,EEP3,EEP4,EEP5,EEP6,EEP7,CNTRL,CNTRL1,
      8CNTRL2,CNTRL3,CNTRL4,CNTRL5,CNTRL6,KNTRL7,CNTRL8,CNTRL9,CNTR10,
      9KNTR11,CNTR12,CNTR13,CNTR14,CNTR15,CNTR16,CNTR17,CNTR18,CNTR19,
      XCNTR54,ERASE,ERAS1,ERAS2,ERAS3,ERAS4,ERAS5,ERAS6,ERAS7,
      XERAS8,ERAS9,ERAS10,ERAS11,ERAS12,ERAS13,ERAS14,ERAS15,ERAS16
        COMMONERAS17,ERAS18,ERAS19,ERAS20,ERAS21,ERAS22,ERAS23,
      1ERAS24,ERAS25,ERAS26,ERAS27,ERAS28,ERAS29,ERAS30,ERAS31,
      2ERAS32,ERAS33,ERAS34,ERAS35,DEC,DEC1,DEC2,DEC3,DEC4,
      3DEC5,DEC6,DEC7,DEC8,DEC9,DEC10,DEC11,KON,CON1,PRT,
      4PRT1,PRT2,PRT3,PRT4,PRT5,PRT6,PRT7,PRT8,PRT9,DEG,
      5TEMP,TEMP1,TEMP2,TEMP3,TEMP4,XI,YI,THI,WI,SMUI,
      6CMUI,STHI,CTHI,SI,KER10,EX1,EX2,C1,C2,C3,C4,C5,C6,
      7C7,C8,C9,C10,C11,C12,C13,C14,C15,C16,C17,C18,C19,C20,
      8C21,C22,C23,C24,C25,C26,C27,C28,C29,C30,SAV,SAV1,
      9SAV2,SAV3,SAV4,SAV5,SAV6,SAV7,SAV8,SAV9,SC1,THCPR,ENEWST,
      XENEWCT,EKP,EKP1,EKP2,EKP3,EKP4,EKP5,ENEWTH,THC1,ENEWM,
      XAA,KAC,NRET,SW2,EN(9),PRNOPT,HOLD,J,K,L,STOR(1000)
        XA=XB
        YA=YB
        THA=THB
```

```
      WA=WB
      SMUA=SMUB
      CMUA=CMUB
      STHA=STHB
      CTHA=CTHB
      SA=SB
      RETURN
      END
$IBFTC MOVCB    REF
      SUBROUTINEMOVCB
      COMMONXA,YA,THA,WA,SMUA,CMUA,STHA,CTHA,SA,XB,YB,THB,
     1WB,SMUB,CMUB,STHB,CTHB,SB,EPB,TEPB,XC,YC,THC,WC,
     2SMUC,CMUC,STHC,CTHC,SC,EPC,TEPC,EMUA,EMUB,EMUC,THAC,
     3WAC,SMUAC,YAC,EMUAC,STHAC,ELAC,THBC,WBC,SMUBC,YBC,EMUBC,
     4STHBC,EPBC,TEPBC,EMBC,TANMA,TANMB,EMC,PC,CPC,EM,THCP,
     5COS1,TAN1,COS2,TAN2,KOUNT,TAPE,ALIGHT,BEGS,SVCON,SVCON1,
     6SVCON2,SVCON3,SVCON4,SVCON5,SVCON6,SVCON7,SVCON8,SVCON9,SVCO10,
     7SVCO11, EEP,EEP1,EEP2,EEP3,EEP4,EEP5,EEP6,EEP7,CNTRL,CNTRL1,
     8CNTRL2,CNTRL3,CNTRL4,CNTRL5,CNTRL6,KNTRL7,CNTRL8,CNTRL9,CNTR10,
     9KNTR11,CNTR12,CNTR13,CNTR14,CNTR15,CNTR16,CNTR17,CNTR18,CNTR19,
     XCNTR54,ERASE,ERAS1,ERAS2,ERAS3,ERAS4,ERAS5,ERAS6,ERAS7,
     XERAS8,ERAS9,ERAS10,ERAS11,ERAS12,ERAS13,ERAS14,ERAS15,ERAS16
      COMMONERAS17,ERAS18,ERAS19,ERAS20,ERAS21,ERAS22,ERAS23,
     1ERAS24,ERAS25,ERAS26,ERAS27,ERAS28,ERAS29,ERAS30,ERAS31,
     2ERAS32,ERAS33,ERAS34,ERAS35,DEC,DEC1,DEC2,DEC3,DEC4,
     3DEC5,DEC6,DEC7,DEC8,DEC9,DEC10,DEC11,KON,CON1,PRT,
     4PRT1,PRT2,PRT3,PRT4,PRT5,PRT6,PRT7,PRT8,PRT9,DEG,
     5TEMP,TEMP1,TEMP2,TEMP3,TEMP4,XI,YI,THI,WI,SMUI,
     6CMUI,STHI,CTHI,SI,KER10,EX1,EX2,C1,C2,C3,C4,C5,C6,
     7C7,C8,C9,C10,C11,C12,C13,C14,C15,C16,C17,C18,C19,C20,
     8C21,C22,C23,C24,C25,C26,C27,C28,C29,C30,SAV,SAV1,
     9SAV2,SAV3,SAV4,SAV5,SAV6,SAV7,SAV8,SAV9,SC1,THCPR,ENEWST,
     XENEWCT,EKP,EKP1,EKP2,EKP3,EKP4,EKP5,ENEWTH,THC1,ENEWM,
     XAA,KAC,NRET,SW2,EN(9),PRNOPT,HOLD,J,K,L,STOR(1000)
      XB=XC
      YB=YC
      THB=THC
      WB=WC
      SMUB=SMUC
      CMUB=CMUC
      STHB=STHC
      CTHB=CTHC
      SB=SC
      RETURN
      END
```

```
$IBFTC WRTSK    REF
       SUBROUTINEWRTSK
       COMMONXA,YA,THA,WA,SMUA,CMUA,STHA,CTHA,SA,XB,YB,THB,
      1WB,SMUB,CMUB,STHB,CTHB,SB,EPB,TEPB,XC,YC,THC,WC,
      2SMUC,CMUC,STHC,CTHC,SC,EPC,TEPC,EMUA,EMUB,EMUC,THAC,
      3WAC,SMUAC,YAC,EMUAC,STHAC,ELAC,THBC,WBC,SMUBC,YBC,EMUBC,
      4STHBC,EPBC,TEPBC,EMBC,TANMA,TANMB,EMC,PC,CPC,EM,THCP,
      5COS1,TAN1,COS2,TAN2,KOUNT,TAPE,ALIGHT,BEGS,SVCON,SVCON1,
      6SVCON2,SVCON3,SVCON4,SVCON5,SVCON6,SVCON7,SVCON8,SVCON9,SVCO10,
      7SVCO11, EEP,EEP1,EEP2,EEP3,EEP4,EEP5,EEP6,EEP7,CNTRL,CNTRL1,
      8CNTRL2,CNTRL3,CNTRL4,CNTRL5,CNTRL6,KNTRL7,CNTRL8,CNTRL9,CNTR10,
      9KNTR11,CNTR12,CNTR13,CNTR14,CNTR15,CNTR16,CNTR17,CNTR18,CNTR19,
      XCNTR54,ERASE,ERAS1,ERAS2,ERAS3,ERAS4,ERAS5,ERAS6,ERAS7,
      XERAS8,ERAS9,ERAS10,ERAS11,ERAS12,ERAS13,ERAS14,ERAS15,ERAS16
       COMMONERAS17,ERAS18,ERAS19,ERAS20,ERAS21,ERAS22,ERAS23,
      1ERAS24,ERAS25,ERAS26,ERAS27,ERAS28,ERAS29,ERAS30,ERAS31,
      2ERAS32,ERAS33,ERAS34,ERAS35,DEC,DEC1,DEC2,DEC3,DEC4,
      3DEC5,DEC6,DEC7,DEC8,DEC9,DEC10,DEC11,KON,CON1,PRT,
      4PRT1,PRT2,PRT3,PRT4,PRT5,PRT6,PRT7,PRT8,PRT9,DEG,
      5TEMP,TEMP1,TEMP2,TEMP3,TEMP4,XI,YI,THI,WI,SMUI,
      6CMUI,STHI,CTHI,SI,KER10,EX1,EX2,C1,C2,C3,C4,C5,C6,
      7C7,C8,C9,C10,C11,C12,C13,C14,C15,C16,C17,C18,C19,C20,
      8C21,C22,C23,C24,C25,C26,C27,C28,C29,C30,SAV,SAV1,
      9SAV2,SAV3,SAV4,SAV5,SAV6,SAV7,SAV8,SAV9,SC1,THCPR,ENEWST,
      XENEWCT,EKP,EKP1,EKP2,EKP3,EKP4,EKP5,ENEWTH,THC1,ENEWM,
      XAA,KAC,NRET,SW2,EN(9),PRNOPT,HOLD,J,K,L,STOR(1000)
       EX1=FPC
       EX2=TEPC
       CALLWRTGN
       RETURN
       END
$IBFTC WRTGN    REF
       SUBROUTINEWRTGN
       COMMONXA,YA,THA,WA,SMUA,CMUA,STHA,CTHA,SA,XB,YB,THB,
      1WB,SMUB,CMUB,STHB,CTHB,SB,EPB,TEPB,XC,YC,THC,WC,
      2SMUC,CMUC,STHC,CTHC,SC,EPC,TEPC,EMUA,EMUB,EMUC,THAC,
      3WAC,SMUAC,YAC,EMUAC,STHAC,ELAC,THBC,WBC,SMUBC,YBC,EMUBC,
      4STHBC,EPBC,TEPBC,EMBC,TANMA,TANMB,EMC,PC,CPC,EM,THCP,
      5COS1,TAN1,COS2,TAN2,KOUNT,TAPE,ALIGHT,BEGS,SVCON,SVCON1,
      6SVCON2,SVCON3,SVCON4,SVCON5,SVCON6,SVCON7,SVCON8,SVCON9,SVCO10,
      7SVCO11, EEP,EEP1,EEP2,EEP3,EEP4,EEP5,EEP6,EEP7,CNTRL,CNTRL1,
      8CNTRL2,CNTRL3,CNTRL4,CNTRL5,CNTRL6,KNTRL7,CNTRL8,CNTRL9,CNTR10,
      9KNTR11,CNTR12,CNTR13,CNTR14,CNTR15,CNTR16,CNTR17,CNTR18,CNTR19,
```

```
      XCNTR54,ERASE,ERAS1,ERAS2,ERAS3,ERAS4,ERAS5,ERAS6,ERAS7,
      XERAS8,ERAS9,ERAS10,ERAS11,ERAS12,ERAS13,ERAS14,ERAS15,ERAS16
       COMMONERAS17,ERAS18,ERAS19,ERAS20,ERAS21,ERAS22,ERAS23,
      1ERAS24,ERAS25,ERAS26,ERAS27,ERAS28,ERAS29,ERAS30,ERAS31,
      2ERAS32,ERAS33,ERAS34,ERAS35,DEC,DEC1,DEC2,DEC3,DEC4,
      3DEC5,DEC6,DEC7,DEC8,DEC9,DEC10,DEC11,KON,CON1,PRT,
      4PRT1,PRT2,PRT3,PRT4,PRT5,PRT6,PRT7,PRT8,PRT9,DEG,
      5TEMP,TEMP1,TEMP2,TEMP3,TEMP4,XI,YI,THI,WI,SMUI,
      6CMUI,STHI,CTHI,SI,KER10,EX1,EX2,C1,C2,C3,C4,C5,C6,
      7C7,C8,C9,C10,C11,C12,C13,C14,C15,C16,C17,C18,C19,C20,
      8C21,C22,C23,C24,C25,C26,C27,C28,C29,C30,SAV,SAV1,
      9SAV2,SAV3,SAV4,SAV5,SAV6,SAV7,SAV8,SAV9,SC1,THCPR,ENEWST,
      XENEWCT,EKP,EKP1,EKP2,EKP3,EKP4,EKP5,ENEWTH,THC1,ENEWM,
      XAA,KAC,NRET,SW2,EN(9),PRNOPT,HOLD,J,K,L,STOR(1000)
       STOR(K)=XC
       STOR(K+1)=YC
       STOR(K+2)=THC
       STOR(K+3)=WC
       STOR(K+4)=SMUC
       STOR(K+5)=CMUC
       STOR(K+6)=STHC
       STOR(K+7)=CTHC
       STOR(K+8)=SC
      K=K+9
      RETURN
      END
$IBFTC SSR        REF
       SUBROUTINESSR
       COMMONXA,YA,THA,WA,SMUA,CMUA,STHA,CTHA,SA,XB,YB,THB,
      1WB,SMUB,CMUB,STHB,CTHB,SB,EPB,TEPB,XC,YC,THC,WC,
      2SMUC,CMUC,STHC,CTHC,SC,EPC,TEPC,EMUA,EMUB,EMUC,THAC,
      3WAC,SMUAC,YAC,EMUAC,STHAC,ELAC,THBC,WBC,SMUBC,YBC,EMUBC,
      4STHBC,EPBC,TEPBC,EMBC,TANMA,TANMB,EMC,PC,CPC,EM,THCP,
      5COS1,TAN1,COS2,TAN2,KOUNT,TAPE,ALIGHT,BEGS,SVCON,SVCON1,
      6SVCON2,SVCON3,SVCON4,SVCON5,SVCON6,SVCON7,SVCON8,SVCON9,SVCO10,
      7SVCO11, EEP,EEP1,EEP2,EEP3,EEP4,EEP5,EEP6,EEP7,CNTRL,CNTRL1,
      8CNTRL2,CNTRL3,CNTRL4,CNTRL5,CNTRL6,KNTRL7,CNTRL8,CNTRL9,CNTR10,
      9KNTR11,CNTR12,CNTR13,CNTR14,CNTR15,CNTR16,CNTR17,CNTR18,CNTR19,
      XCNTR54,ERASE,ERAS1,ERAS2,ERAS3,ERAS4,ERAS5,ERAS6,ERAS7,
      XERAS8,ERAS9,ERAS10,ERAS11,ERAS12,ERAS13,ERAS14,ERAS15,ERAS16
       COMMONERAS17,ERAS18,ERAS19,ERAS20,ERAS21,ERAS22,ERAS23,
      1ERAS24,ERAS25,ERAS26,ERAS27,ERAS28,ERAS29,ERAS30,ERAS31,
      2ERAS32,ERAS33,ERAS34,ERAS35,DEC,DEC1,DEC2,DEC3,DEC4,
      3DEC5,DEC6,DEC7,DEC8,DEC9,DEC10,DEC11,KON,CON1,PRT,
      4PRT1,PRT2,PRT3,PRT4,PRT5,PRT6,PRT7,PRT8,PRT9,DEG,
```

```
      5TEMP,TEMP1,TEMP2,TEMP3,TEMP4,XI,YI,THI,WI,SMUI,
      6CMUI,STHI,CTHI,SI,KER10,EX1,EX2,C1,C2,C3,C4,C5,C6,
      7C7,C8,C9,C10,C11,C12,C13,C14,C15,C16,C17,C18,C19,C20,
      8C21,C22,C23,C24,C25,C26,C27,C28,C29,C30,SAV,SAV1,
      9SAV2,SAV3,SAV4,SAV5,SAV6,SAV7,SAV8,SAV9,SC1,THCPR,ENEWST,
      XENEWCT,EKP,EKP1,EKP2,EKP3,EKP4,EKP5,ENEWTH,THC1,ENEWM,
      XAA,KAC,NRET,SW2,EN(9),PRNOPT,HOLD,J,K,L,STOR(1000)
        ERAS1=CNTRL3+CNTRL3
        ERAS2=CNTRL3+DEC1
        ERAS3=CNTRL3-DEC1
        ERAS4=ERAS3/ERAS1
        IF(HOLD)3,2,2
      3 ERAS5=EKP5*ERASE
        GOTO1
      2 ERAS5=EEP5*ERASE
      1 ERAS4=((ERAS5-ERAS4)/ERAS2)*ERAS1
        ERAS1=ERAS3/DEC2
        ERAS5=DEC1/ERAS5
        ERAS1=((ERAS5+ERAS1)/ERAS2)*DEC2
        ERAS1=ALOG(ERAS1)*CNTRL3
        SC=((ALOG(ERAS4)+ERAS1)/ERAS3)*CNTRL5
        RETURN
        END
$IBFTC SPACE    REF
        SUBROUTINE SPACE
        COMMONXA,YA,THA,WA,SMUA,CMUA,STHA,CTHA,SA,XB,YB,THB,
      1WB,SMUB,CMUB,STHB,CTHB,SB,EPB,TEPB,XC,YC,THC,WC,
      2SMUC,CMUC,STHC,CTHC,SC,EPC,TEPC,EMUA,EMUB,EMUC,THAC,
      3WAC,SMUAC,YAC,EMUAC,STHAC,ELAC,THBC,WBC,SMUBC,YBC,EMUBC,
      4STHBC,EPBC,TEPBC,EMBC,TANMA,TANMB,EMC,PC,CPC,EM,THCP,
      5COS1,TAN1,COS2,TAN2,KOUNT,TAPE,ALIGHT,BEGS,SVCON,SVCON1,
      6SVCON2,SVCON3,SVCON4,SVCON5,SVCON6,SVCON7,SVCON8,SVCON9,SVCO10,
      7SVCO11,  EEP,EEP1,EEP2,EEP3,EEP4,EEP5,EEP6,EEP7,CNTRL,CNTRL1,
      8CNTRL2,CNTRL3,CNTRL4,CNTRL5,CNTRL6,KNTRL7,CNTRL8,CNTRL9,CNTR10,
      9KNTR11,CNTR12,CNTR13,CNTR14,CNTR15,CNTR16,CNTR17,CNTR18,CNTR19,
      XCNTR54,ERASE,ERAS1,ERAS2,ERAS3,ERAS4,ERAS5,ERAS6,ERAS7,
      XERAS8,ERAS9,ERAS10,ERAS11,ERAS12,ERAS13,ERAS14,ERAS15,ERAS16
        COMMONERAS17,ERAS18,ERAS19,ERAS20,ERAS21,ERAS22,ERAS23,
      1ERAS24,ERAS25,ERAS26,ERAS27,ERAS28,ERAS29,ERAS30,ERAS31,
      2ERAS32,ERAS33,ERAS34,ERAS35,DEC,DEC1,DEC2,DEC3,DEC4,
      3DEC5,DEC6,DEC7,DEC8,DEC9,DEC10,DEC11,KON,CON1,PRT,
      4PRT1,PRT2,PRT3,PRT4,PRT5,PRT6,PRT7,PRT8,PRT9,DEG,
      5TEMP,TEMP1,TEMP2,TEMP3,TEMP4,XI,YI,THI,WI,SMUI,
```

```
      6CMUI,STHI,CTHI,SI,KER10,EX1,EX2,C1,C2,C3,C4,C5,C6,
      7C7,C8,C9,C10,C11,C12,C13,C14,C15,C16,C17,C18,C19,C20,
      8C21,C22,C23,C24,C25,C26,C27,C28,C29,C30,SAV,SAV1,
      9SAV2,SAV3,SAV4,SAV5,SAV6,SAV7,SAV8,SAV9,SC1,THCPR,ENEWST,
      XENEWCT,EKP,EKP1,EKP2,EKP3,EKP4,EKP5,ENEWTH,THC1,ENEWM,
      XAA,KAC,NRET,SW2,EN(9),PRNOPT,HOLD,J,K,L,STOR(1000)
       WRITE(6,100)
 100   FORMAT (1H //)
       RETURN
       END
$IBFTC GEN      REF
       SUBROUTINEGEN
       COMMONXA,YA,THA,WA,SMUA,CMUA,STHA,CTHA,SA,XB,YB,THB,
      1WB,SMUB,CMUB,STHB,CTHB,SB,EPB,TEPB,XC,YC,THC,WC,
      2SMUC,CMUC,STHC,CTHC,SC,EPC,TEPC,EMUA,EMUB,EMUC,THAC,
      3WAC,SMUAC,YAC,EMUAC,STHAC,ELAC,THBC,WBC,SMUBC,YBC,EMUBC,
      4STHBC,EPBC,TEPBC,EMBC,TANMA,TANMB,EMC,PC,CPC,EM,THCP,
      5COS1,TAN1,COS2,TAN2,KOUNT,TAPE,ALIGHT,BEGS,SVCON,SVCON1,
      6SVCON2,SVCON3,SVCON4,SVCON5,SVCON6,SVCON7,SVCON8,SVCON9,SVCO10,
      7SVCO11, EEP,EEP1,EEP2,EEP3,EEP4,EEP5,EEP6,EEP7,CNTRL,CNTRL1,
      8CNTRL2,CNTRL3,CNTRL4,CNTRL5,CNTRL6,KNTRL7,CNTRL8,CNTRL9,CNTR10,
      9KNTR11,CNTR12,CNTR13,CNTR14,CNTR15,CNTR16,CNTR17,CNTR18,CNTR19,
      XCNTR54,ERASE,ERAS1,ERAS2,ERAS3,ERAS4,ERAS5,ERAS6,ERAS7,
      XERAS8,ERAS9,ERAS10,ERAS11,ERAS12,ERAS13,ERAS14,ERAS15,ERAS16
       COMMONERAS17,ERAS18,ERAS19,ERAS20,ERAS21,ERAS22,ERAS23,
      1ERAS24,ERAS25,ERAS26,ERAS27,ERAS28,ERAS29,ERAS30,ERAS31,
      2ERAS32,ERAS33,ERAS34,ERAS35,DEC,DEC1,DEC2,DEC3,DEC4,
      3DEC5,DEC6,DEC7,DEC8,DEC9,DEC10,DEC11,KON,CON1,PRT,
      4PRT1,PRT2,PRT3,PRT4,PRT5,PRT6,PRT7,PRT8,PRT9,DEG,
      5TEMP,TEMP1,TEMP2,TEMP3,TEMP4,XI,YI,THI,WI,SMUI,
      6CMUI,STHI,CTHI,SI,KER10,EX1,EX2,C1,C2,C3,C4,C5,C6,
      7C7,C8,C9,C10,C11,C12,C13,C14,C15,C16,C17,C18,C19,C20,
      8C21,C22,C23,C24,C25,C26,C27,C28,C29,C30,SAV,SAV1,
      9SAV2,SAV3,SAV4,SAV5,SAV6,SAV7,SAV8,SAV9,SC1,THCPR,ENEWST,
      XENEWCT,EKP,EKP1,EKP2,EKP3,EKP4,EKP5,ENEWTH,THC1,ENEWM,
      XAA,KAC,NRET,SW2,EN(9),PRNOPT,HOLD,J,K,L,STOR(1000)
       COMMON LTEST
       THAC=THA
       THCP=0
       THBC=THB
       KOUNT=0
       WBC=WB
       WAC=WA
       TANMA=SMUA/CMUA
       EMUA=ATAN(TANMA)
```

```
      EMUAC=EMUA
      TANMB=SMUB/CMUB
      EMUB=ATAN(TANMB)
      EMUBC=EMUB
 19   ERASE=THAC+EMUAC
      COS1=COS(ERASE)
      TAN1=SIN(ERASE)/COS1
      ERASE=THBC-EMUBC
      COS2=COS(ERASE)
      TAN2=SIN(ERASE)/COS2
      ERASE=TAN1-TAN2
      ERAS1=TAN1*XA
      XC=(-TAN2*XB+YB+ERAS1-YA)/ERASE
      ERAS4=XC-XA
      YC=TAN1*ERAS4+YA
      YAC=(YC+YA)/DEC2
      YBC=(YB+YC)/DEC2
      ERASE=COS(EMUAC)
      SMUAC=SIN(EMUAC)
      TANMA=SMUAC/ERASE
      ERASE=COS(EMUBC)
      SMUBC=SIN(EMUBC)
      TANMB=SMUBC/ERASE
      CALLSLITET(2,LTEST)
      GOTO(1,3),LTEST
  1   CALLSLITE(2)
      IF(CNTRL9)4,3,4
  4   ERASF=ERAS4*SMUAC
      ERASE=COS1/ERASE
      ERAS1=XC-XB
      FRAS1=SMUBC*ERAS1
      ERAS1=COS2/ERAS1
      ERAS3=ERASE+ERAS1
      ERASE=ERASE*SA
      SC=(ERAS1*SB+ERASE)/ERAS3
      GOTO5
  3   SC=SB
  5   ERASE=WAC*TANMA
      ERAS1=WBC*TANMB
      ERAS5=CNTRL3*CNTRL5
      ERAS3=SC-SA
      ERAS2=((ERAS3*SMUAC)/ERAS5)*SMUAC
      ERAS3=SC-SB
```

```
      ERAS3=((ERAS3*SMUBC)/ERAS5)*SMUBC
      ERAS6=TANMA*THA
      ERAS7=TANMB*THB
      IF(CNTRL8)7,6,7
   7  STHAC=SIN(THAC)
      STHBC=SIN(THBC)
      ELAC=((SMUAC*TANMA)/COS1)*STHAC
      EMBC=((SMUBC*TANMB)/COS2)*STHBC
      IF(YAC+YBC)9,8,9
   9  IF(YAC)11,10,11
  11  IF(YBC)13,12,13
  12  ERAS8=ERAS1+ERAS1+ERASE
      ERAS9=(ERAS7+ERAS7-ERAS3)*WBC+WB
      ERAS4=((XC-XA)/YAC)*ELAC
      ERAS10=-ERAS2-ERAS6+ERAS4
      THC=(-(ERAS10*WAC+WA)+ERAS9)/ERAS8
      WC=(THC*TANMA+ERAS10)*WAC+WA
      GOTO14
  10  ERAS8=ERASE+ERASE+ERAS1
      ERAS5=((XC-XB)/YBC)*EMBC
      ERAS9=(ERAS7+ERAS5-ERAS3)*WBC+WB
      ERAS10=-ERAS6-ERAS6-ERAS2
      THC=(-(ERAS10*WAC+WA)+ERAS9)/ERAS8
      ERAS8=THC*TANMA
      WC=(ERAS8+ERAS8+ERAS10)*WAC+WA
      GOTO14
   8  ERAS8=ERASE+ERAS1+ERASE+ERAS1
      ERAS9=(ERAS7+ERAS7-ERAS3)*WBC+WB
      ERAS10=-ERAS6-ERAS6-ERAS2
      THC=(-(ERAS10*WAC+WA)+ERAS9)/ERAS8
      ERAS8=THC*TANMA
      WC=(ERAS8+ERAS8+ERAS10)*WAC+WA
      GOTO14
   6  ERAS4=0
      ERAS5=0
      GOTO15
  13  ERAS4=((XC-XA)/YAC)*ELAC
      ERAS5=((XC-XB)/YBC)*EMBC
  15  ERAS8=ERASE+ERAS1
      ERAS9=(ERAS7+ERAS5-ERAS3)*WBC+WB
      ERAS10=ERAS4-ERAS6-ERAS2
      THC=(-(ERAS10*WAC+WA)+ERAS9)/ERAS8
      WC=(THC*TANMA+ERAS10)*WAC+WA
  14  CALLMUSR
      IF(DEC)21,20,21
```

```
20    KOUNT=KOUNT+KON
      IF(KOUNT-KNTRL7)17,16,16
  16  IF(ABS(THC-THCP)-CNTRL6)18,17,17
  17  THBC=(THB+THC)/DEC2
      WBC=(WB+WC)/DEC2
      EMUBC=(EMUB+EMUC)/DEC2
      THAC=(THA+THC)/DEC2
      WAC=(WA+WC)/DEC2
      EMUAC=(EMUA+EMUC)/DEC2
      THCP=THC
      GOTO19
  18  STHC=SIN(THC)
      CTHC=COS(THC)
 21   RETURN
      END
$IBFTC WRTFL    REF
      SUBROUTINEWRTFL
      COMMONXA,YA,THA,WA,SMUA,CMUA,STHA,CTHA,SA,XB,YB,THB,
     1WB,SMUB,CMUB,STHB,CTHB,SB,EPB,TEPB,XC,YC,THC,WC,
     2SMUC,CMUC,STHC,CTHC,SC,EPC,TEPC,EMUA,EMUB,EMUC,THAC,
     3WAC,SMUAC,YAC,EMUAC,STHAC,ELAC,THBC,WBC,SMUBC,YBC,EMUBC,
     4STHBC,EPBC,TEPBC,EMBC,TANMA,TANMB,EMC,PC,CPC,EM,THCP,
     5COS1,TAN1,COS2,TAN2,KOUNT,TAPE,ALIGHT,BEGS,SVCON,SVCON1,
     6SVCON2,SVCON3,SVCON4,SVCON5,SVCON6,SVCON7,SVCON8,SVCON9,SVCO10,
     7SVCO11, EEP,EEP1,EEP2,EEP3,EEP4,EEP5,EEP6,EEP7,CNTRL,CNTRL1,
     8CNTRL2,CNTRL3,CNTRL4,CNTRL5,CNTRL6,KNTRL7,CNTRL8,CNTRL9,CNTR10,
     9KNTR11,CNTR12,CNTR13,CNTR14,CNTR15,CNTR16,CNTR17,CNTR18,CNTR19,
     XCNTR54,ERASE,ERAS1,ERAS2,ERAS3,ERAS4,ERAS5,ERAS6,ERAS7,
     XERAS8,ERAS9,ERAS10,ERAS11,ERAS12,ERAS13,ERAS14,ERAS15,ERAS16
      COMMONERAS17,ERAS18,ERAS19,ERAS20,ERAS21,ERAS22,ERAS23,
     1ERAS24,ERAS25,ERAS26,ERAS27,ERAS28,ERAS29,ERAS30,ERAS31,
     2ERAS32,ERAS33,ERAS34,ERAS35,DEC,DEC1,DEC2,DEC3,DEC4,
     3DEC5,DEC6,DEC7,DEC8,DEC9,DEC10,DEC11,KON,CON1,PRT,
     4PRT1,PRT2,PRT3,PRT4,PRT5,PRT6,PRT7,PRT8,PRT9,DEG,
     5TEMP,TEMP1,TEMP2,TEMP3,TEMP4,XI,YI,THI,WI,SMUI,
     6CMUI,STHI,CTHI,SI,KER10,EX1,EX2,C1,C2,C3,C4,C5,C6,
     7C7,C8,C9,C10,C11,C12,C13,C14,C15,C16,C17,C18,C19,C20,
     8C21,C22,C23,C24,C25,C26,C27,C28,C29,C30,SAV,SAV1,
     9SAV2,SAV3,SAV4,SAV5,SAV6,SAV7,SAV8,SAV9,SC1,THCPR,ENEWST,
     XENEWCT,EKP,EKP1,EKP2,EKP3,EKP4,EKP5,ENEWTH,THC1,ENEWM,
     XAA,KAC,NRET,SW2,EN(9),PRNOPT,HOLD,J,K,L,STOR(1000)
      COMMON LTEST
      K=1
```

```
      J=1
      TAPE=-TAPE
      CALLSLITET(2,LTEST)
      GOTO(1,3),LTEST
    3 RETURN
    1 CALLSLITE(2)
      ALIGHT=DEC1
      RETURN
      END
$IBFTC RDA       REF
      SUBROUTINERDA
      COMMONXA,YA,THA,WA,SMUA,CMUA,STHA,CTHA,SA,XB,YB,THB,
     1WB,SMUB,CMUB,STHB,CTHB,SB,EPB,TEPB,XC,YC,THC,WC,
     2SMUC,CMUC,STHC,CTHC,SC,EPC,TEPC,EMUA,EMUB,EMUC,THAC,
     3WAC,SMUAC,YAC,EMUAC,STHAC,ELAC,THBC,WBC,SMUBC,YBC,EMUBC,
     4STHBC,EPBC,TEPBC,EMBC,TANMA,TANMB,EMC,PC,CPC,EM,THCP,
     5COS1,TAN1,COS2,TAN2,KOUNT,TAPE,ALIGHT,BEGS,SVCON,SVCON1,
     6SVCON2,SVCON3,SVCON4,SVCON5,SVCON6,SVCON7,SVCON8,SVCON9,SVCO10,
     7SVCO11, EEP,EEP1,EEP2,EEP3,EEP4,EEP5,EEP6,EEP7,CNTRL,CNTRL1,
     8CNTRL2,CNTRL3,CNTRL4,CNTRL5,CNTRL6,KNTRL7,CNTRL8,CNTRL9,CNTR10,
     9KNTR11,CNTR12,CNTR13,CNTR14,CNTR15,CNTR16,CNTR17,CNTR18,CNTR19,
     XCNTR54,ERASE,ERAS1,ERAS2,ERAS3,ERAS4,ERAS5,ERAS6,ERAS7,
     XERAS8,ERAS9,ERAS10,ERAS11,ERAS12,ERAS13,ERAS14,ERAS15,ERAS16
      COMMONERAS17,ERAS18,ERAS19,ERAS20,ERAS21,ERAS22,ERAS23,
     1ERAS24,ERAS25,ERAS26,ERAS27,ERAS28,ERAS29,ERAS30,ERAS31,
     2ERAS32,ERAS33,ERAS34,ERAS35,DEC,DEC1,DEC2,DEC3,DEC4,
     3DEC5,DEC6,DEC7,DEC8,DEC9,DEC10,DEC11,KON,CON1,PRT,
     4PRT1,PRT2,PRT3,PRT4,PRT5,PRT6,PRT7,PRT8,PRT9,DEG,
     5TEMP,TEMP1,TEMP2,TEMP3,TEMP4,XI,YI,THI,WI,SMUI,
     6CMUI,STHI,CTHI,SI,KER10,EX1,EX2,C1,C2,C3,C4,C5,C6,
     7C7,C8,C9,C10,C11,C12,C13,C14,C15,C16,C17,C18,C19,C20,
     8C21,C22,C23,C24,C25,C26,C27,C28,C29,C30,SAV,SAV1,
     9SAV2,SAV3,SAV4,SAV5,SAV6,SAV7,SAV8,SAV9,SC1,THCPR,ENEWST,
     XENEWCT,EKP,EKP1,EKP2,EKP3,EKP4,EKP5,ENEWTH,THC1,ENEWM,
     XAA,KAC,NRET,SW2,EN(9),PRNOPT,HOLD,J,K,L,STOR(1000)
      IF(STOR(J+3))2,1,2
    2 XA=STOR(J)
      YA=STOR (J+1)
      THA=STOR (J+2)
      WA=STOR (J+3)
      SMUA=STOR (J+4)
      CMUA=STOR (J+5)
      STHA=STOR (J+6)
      CTHA=STOR (J+7)
      SA=STOR (J+8)
```

APPENDIX

```
      J=J+9
      NRET=2
      RETURN
    1 KAC=KNTR11+KON-KER10
      KER10=0
      NRET=1
      RETURN
      END
$IBFTC RDB       REF
      SUBROUTINERDB
      COMMONXA,YA,THA,WA,SMUA,CMUA,STHA,CTHA,SA,XB,YB,THB,
     1WB,SMUB,CMUB,STHB,CTHB,SB,EPB,TEPB,XC,YC,THC,WC,
     2SMUC,CMUC,STHC,CTHC,SC,EPC,TEPC,EMUA,EMUB,EMUC,THAC,
     3WAC,SMUAC,YAC,EMUAC,STHAC,ELAC,THBC,WBC,SMUBC,YBC,EMUBC,
     4STHBC,EPBC,TEPBC,EMBC,TANMA,TANMB,EMC,PC,CPC,EM,THCP,
     5COS1,TAN1,COS2,TAN2,KOUNT,TAPE,ALIGHT,BEGS,SVCON,SVCON1,
     6SVCON2,SVCON3,SVCON4,SVCON5,SVCON6,SVCON7,SVCON8,SVCON9,SVCO10,
     7SVCO11, EEP,EEP1,EEP2,EEP3,EEP4,EEP5,EEP6,EEP7,CNTRL,CNTRL1,
     8CNTRL2,CNTRL3,CNTRL4,CNTRL5,CNTRL6,KNTRL7,CNTRL8,CNTRL9,CNTR10,
     9KNTR11,CNTR12,CNTR13,CNTR14,CNTR15,CNTR16,CNTR17,CNTR18,CNTR19,
     XCNTR54,ERASE,ERAS1,ERAS2,ERAS3,ERAS4,ERAS5,ERAS6,ERAS7,
     XERAS8,ERAS9,ERAS10,ERAS11,ERAS12,ERAS13,ERAS14,ERAS15,ERAS16
      COMMONERAS17,ERAS18,ERAS19,ERAS20,ERAS21,ERAS22,ERAS23,
     1ERAS24,ERAS25,ERAS26,ERAS27,ERAS28,ERAS29,ERAS30,ERAS31,
     2ERAS32,ERAS33,ERAS34,ERAS35,DEC,DEC1,DEC2,DEC3,DEC4,
     3DEC5,DEC6,DEC7,DEC8,DEC9,DEC10,DEC11,KON,CON1,PRT,
     4PRT1,PRT2,PRT3,PRT4,PRT5,PRT6,PRT7,PRT8,PRT9,DEG,
     5TEMP,TEMP1,TEMP2,TEMP3,TEMP4,XI,YI,THI,WI,SMUI,
     6CMUI,STHI,CTHI,SI,KER10,EX1,EX2,C1,C2,C3,C4,C5,C6,
     7C7,C8,C9,C10,C11,C12,C13,C14,C15,C16,C17,C18,C19,C20,
     8C21,C22,C23,C24,C25,C26,C27,C28,C29,C30,SAV,SAV1,
     9SAV2,SAV3,SAV4,SAV5,SAV6,SAV7,SAV8,SAV9,SC1,THCPR,ENEWST,
     XENEWCT,EKP,EKP1,EKP2,EKP3,EKP4,EKP5,ENEWTH,THC1,ENEWM,
     XAA,KAC,NRET,SW2,EN(9),PRNOPT,HOLD,J,K,L,STOR(1000)
      EPB=EX1
      TEPB=EX2
      KER10=KER10+KON
      IF(STOR(J+3))2,1,2
    2 XB=STOR(J)
      YB=STOR(J+1)
      THB=STOR(J+2)
      WB=STOR(J+3)
      SMUB=STOR(J+4)
```

63

```
      CMUB=STOR(J+5)
      STHB=STOR(J+6)
      CTHB=STOR(J+7)
      SB=STOR(J+8)
      J=J+9
      GOTO4
   1  KAC=KNTR11+KON-KER10
      KER10=0
      GOTO3
   4  NRET=2
      RETURN
   3  NRET=1
      RETURN
      END
```

# REFERENCES

1. Williams, R. L.:  Analytical and Experimental Investigations of a Two-Dimensional Variable Geometry Inlet for Integral Installation on Hypersonic Air Vehicles. Rept. No. 5902 (Contract AF 33(657)-8626), The Marquardt Corporation, July 31, 1962.

2. Gunther, Fred C.; and Carr, John H.:  Development of an Adjustable Supersonic Inlet Utilizing Complete Boundary-Layer Removal at the Throat.  Progr. Rept. No. 20-321 (Contract No. DA-04-495-Ord 18), Jet Propulsion Lab. (California Inst. Technol.), June 14, 1957.

3. Henry, John R.; Mackley, Ernest A.; and Torrence, Marvin G.:  Investigation of the Compression Field and the Flow Distribution in the Throat of a Two-Dimensional, Internal-Compression, Mach Number 6.9 Inlet.  NASA TM X-605, 1961.

4. Stitt, Leonard E.; and Obery, Leonard J.:  Performance of an All-Internal Conical Compression Inlet With Annular Throat Bleed at Mach Number 5.0.  NACA RM E58E14, 1958.

5. Sterrett, James R.; and Emery, James C.:  Extension of Boundary-Layer-Separation Criteria to a Mach Number of 6.5 by Utilizing Flat Plates With Forward-Facing Steps.  NASA TN D-618, 1960.

6. Connors, James F.; and Woollett, Richard R.:  Preliminary Investigation of an Asymmetric Swept Nose Inlet of Circular Projection at Mach Number 3.85.  NACA RM E54G26, 1954.

7. McCracken, Daniel D.:  A Guide to FORTRAN Programming.  John Wiley & Sons, Inc., c.1961.

8. Ferri, Antonio:  Application of the Method of Characteristics to Supersonic Rotational Flow.  NACA Rep. 841, 1946.  (Supersedes NACA TN 1135.)

Figure 1.- General view of inlet model. L-62-8208



Figure 2.- Inlet model with starting flap open. L-61-1952

66

Side view: section through model center line

(a) Basic model.

Figure 3.- General arrangement and principal dimensions of model. All dimensions are in centimeters.

Boundary—layer
bleed slot

To combination
plug — venturi

5.286

Station 0

Station
19.657

Station
21.059

Station
26.327

Station
35.334

Station
54.013

Station
66.421

Supersonic
diffuser

Throat

Subsonic
diffuser

Total—pressure
measuring station

(b) Configuration I.

Station
19.812

Station
19.657

15°

Details of bleed slot
Configuration I

Serrations:
.254 point to point
.318 deep

.508 R

Details of bleed slot
Configuration II

Boundary—layer
bleed slot

To combination
plug — venturi

5.286

Station 0

Station
19.657

Station
21.059

Station
26.327

Station
35.334

Station
54.013

Station
66.421

Supersonic
diffuser

Throat

Subsonic
diffuser

Total—pressure
measuring station

(c) Configuration II.

Figure 3.- Continued.

(d) Configuration III.

Section view of throat
at perforations

Configuration III

Details of bleed slot
Configuration IV



(e) Configuration IV.

Figure 3.- Concluded.

Figure 4.- Area distribution within model.

(a) Theoretical, design condition.

Figure 5.- Longitudinal static-pressure distribution through supersonic diffuser, throat, and subsonic diffuser.

(b) Configuration 1.

Figure 5.- Continued.

Distance from inlet lip, centimeters

(c) Configuration II.

Figure 5.- Continued.

(d) Configuration III.

Figure 5.- Continued.

The chart shows $\frac{p}{p_{t,\infty}}$ plotted against Distance from inlet lip, centimeters.

| $\frac{\overline{p_t}}{p_{t,\infty}}$ | $\frac{w}{w_\infty}$ |
|---|---|
| .1868 | .888 |
| .1831 | .908 |
| .1771 | .907 |
| .1700 | .908 |
| .1642 | .902 |
| .1545 | .901 |
| .1452 | .893 |
| .1150 | .867 |
| .0960 | .856 |

(e) Configuration IV.

Figure 5.- Concluded.

75

$$\frac{\overline{p_t}}{p_{t,\infty}} = .1056 \qquad \frac{w}{w_\infty} = .8193$$

.1070
.1060
.1050
.1040

Supercritical

$$\frac{\overline{p_t}}{p_{t,\infty}} = .1295 \qquad \frac{w}{w_\infty} = .8308$$

.1110
.1300
.1290
.1280

Supercritical

$$\frac{\overline{p_t}}{p_{t,\infty}} = .1523 \qquad \frac{w}{w_\infty} = .8667$$

.1530
.1520

Critical

$$\frac{\overline{p_t}}{p_{t,\infty}} = .0647 \qquad \frac{w}{w_\infty} = .3441$$

.0650
.0640

Subcritical, flap closed

(a) Configuration I.

Figure 6.- Total-pressure contours downstream of subsonic diffuser.

$$\frac{\overline{p_t}}{p_{t,\infty}} = .1102 \qquad \frac{w}{w_\infty} = .8314$$

.1120

.1110

.1100

.1090

.1080

Supercritical

$$\frac{\overline{p_t}}{p_{t,\infty}} = .1383 \qquad \frac{w}{w_\infty} = .8507$$

.1390

.1380

.1370

.1360

.1400

Supercritical

$$\frac{\overline{p_t}}{p_{t,\infty}} = .1575 \qquad \frac{w}{w_\infty} = .8707$$

.1580

Critical

(b) Configuration II.

Figure 6.- Continued.

$$\frac{\overline{p_t}}{p_{t,\infty}} = .1076 \qquad \frac{w}{w_\infty} = .8147$$



Supercritical

$$\frac{\overline{p_t}}{p_{t,\infty}} = .1349 \qquad \frac{w}{w_\infty} = .8289$$



Supercritical

$$\frac{\overline{p_t}}{p_{t,\infty}} = .1697 \qquad \frac{w}{w_\infty} = .8438$$



Critical

$$\frac{\overline{p_t}}{p_{t,\infty}} = .1701 \qquad \frac{w}{w_\infty} = .6981$$



Subcritical, flap open

(c) Configuration III.

Figure 6.- Continued.

$\dfrac{\overline{p_t}}{p_{t,\infty}} = .1150 \qquad \dfrac{w}{w_\infty} = .8669$

.1180

.1170

.1160

.1150

.1140

.1130

Supercritical

$\dfrac{\overline{p_t}}{p_{t,\infty}} = .1642 \qquad \dfrac{w}{w_\infty} = .9018$

.1650

.1640

.1630

Supercritical

$\dfrac{\overline{p_t}}{p_{t,\infty}} = .1868 \qquad \dfrac{w}{w_\infty} = .8877$

.1880

.1870

Critical

$\dfrac{\overline{p_t}}{p_{t,\infty}} = .1738 \qquad \dfrac{w}{w_\infty} = .6007$

.1740

.1730

Subcritical, flap open

(d) Configuration IV.

Figure 6.- Concluded.

Figure 7.- Variation of total-pressure ratio with mass-flow ratio.

Figure 8.- Variation of kinetic-energy efficiency with mass-flow ratio.

# NASA SCIENTIFIC AND TECHNICAL PUBLICATIONS

**TECHNICAL REPORTS:** Scientific and technical information considered important, complete, and a lasting contribution to existing knowledge.

**TECHNICAL NOTES:** Information less broad in scope but nevertheless of importance as a contribution to existing knowledge.

**TECHNICAL MEMORANDUMS:** Information receiving limited distribution because of preliminary data, security classification, or other reasons.

**CONTRACTOR REPORTS:** Technical information generated in connection with a NASA contract or grant and released under NASA auspices.

**TECHNICAL TRANSLATIONS:** Information published in a foreign language considered to merit NASA distribution in English.

**TECHNICAL REPRINTS:** Information derived from NASA activities and initially published in the form of journal articles.

**SPECIAL PUBLICATIONS:** Information derived from or of value to NASA activities but not necessarily reporting the results of individual NASA-programmed scientific efforts. Publications include conference proceedings, monographs, data compilations, handbooks, sourcebooks, and special bibliographies.

*Details on the availability of these publications may be obtained from:*

SCIENTIFIC AND TECHNICAL INFORMATION DIVISION

# NATIONAL AERONAUTICS AND SPACE ADMINISTRATION

Washington, D.C. 20546